

Boot Options & OS Versions

Mobile Products – Current and Legacy

Product CE OS WM OS	WARM BOOT	COLD BOOT	CLEAN BOOT
ELF CE60=1.90 WM65=1.90	Yellow + Blue + Red Phone	Hold down Scan then Reset under battery	Cold / Red Phone + 0
LYNX WM65=1.86	Yellow + Blue + Red Phone	Reset under battery	Warm / Red Phone + 0
FALCON X3 CE60=1.90 WM65=1.90	Yellow + Blue + ESC	Hold down Scan then Reset under battery	Cold / ESC + 0
FALCON X3 Plus CE60=1.92 WM65=1.92	Yellow + Blue + ESC	Hold down Scan then Reset under battery	Cold / ESC + 0
MEMOR CE50 = 4.40 WM61 = 4.40	ESC + Power	ESC + Toggle + Power	Cold / ESC + 0
MEMOR X3 WinCore and Pro: 1.00.23	ESC + Power	ESC + Enter + Power	Cold / ESC + 0
SKORPIO CE50=3.30 WM61=3.30	Yellow + Blue + Scan	Yellow + Dn Arrow + Blue + Scan	Cold / ESC + 0
SKORPIO X3 CE60=1.90 WM65=1.90	Yellow + Blue + ESC	Hold down Scan then Reset under battery	Cold / ESC + 0
KYMAN CE50=3.30 WM61=3.30	F1 + Scan + Power	F1 + F2 + Scan + Power	Cold / ESC + 0

Product CE OS WM OS	WARM BOOT	COLD BOOT	CLEAN BOOT
RHINO CE6.0 = 1.2.2	Windows directory Run Reboot Command Or Remove upper left panel and press the push button	Windows directory Run Cold Reboot Command	Warm or Cold Boot then press and hold UP + DOWN keys until the touch calibration screen appears
JOYA X1 / X2 / A	Press the "+" (plus) and "-" (minus) keys simultaneously for 5 seconds	Lightly press a metallic clip inside the circle hole on the back.	Cold boot and immediately press and hold "=" and "-". Press "e" when pop up box appears
FALCON 4400 26 Key CE50=3.16 WM5=3.19	FN + ALPHA + BKSP	Paper Clip + Power	CE: Delete all files in 'FlashFX Disk' / Cold Boot WM: Warm Boot / ESC + 0
FALCON 4400 48 Key CE50=3.16 WM5=3.19	CTRL + ALT + BKSP	Paper Clip + Power	CE = Delete all files in 'FlashFX Disk' / coldboot WM: Warm Boot / ESC + 0
FALCON 4400 52 Key CE50=3.16 WM5=3.19	ALT + FN + F1	Paper Clip + Power	CE = Delete all files in 'FlashFX Disk' / Cold Boot WM: Warm Boot / ESC + 0

Product CE OS WM OS	WARM BOOT	COLD BOOT	CLEAN BOOT	SAFE BOOT
FALCON 4400 52NU Key CE50=3.16 WM5=3.19	CTRL + ALT + DEL	Paper Clip + Power	CE = Delete all files in 'FlashFX Disk' / Cold Boot WM: Warm Boot / ESC + 0	FALCON 4400 52NU Key CE50=3.16 WM5=3.19
FALCON 31X	CTL + ALT + DEL	Short pins under card OR ALT + FN2 +PWR	Type Format [ENTER] at C prompt	Warm or Cold boot + (ESC + DEL)
FALCON 32X	CTL + ALT + DEL	Short pins under card	Type Format [ENTER] at C prompt	Warm or Cold boot + (ESC + DEL)
FALCON 33X 25 Key	LAMP + FN + BACKSPACE	Paperclip	Type Format [ENTER] at C prompt	Paperclip – when “Waiting...” appears press ESC + TAB
FALCON 33X 38 Key	CTL + ALT + DEL	Paperclip	Type Format [ENTER] at C prompt	Paperclip – when “Waiting...” appears press ESC + SPACE
PEGASO CE50=3.14 WM60=3.16	AZ + ESC + 3	Reset under battery	Warm / ESC + 0	Cold boot, then hold ESC + 5

Product CE OS WM OS	WARM BOOT	COLD BOOT	CLEAN BOOT	SAFE BOOT
FALCON 4220 CE42=4.10	Reset Button	Reset Button + F2	FORMAT/ PARTITION OR Delete Reg1 and Reg 2 – Cold Boot	Cold boot then hold F1 to Desktop
FALCON 34X 25 Key	LAMP + FN + BACKSPACE	Paperclip	Type Format [ENTER] at C prompt	Paperclip – when “Waiting...” appears press ESC + TAB
FALCON 34X 38 Key	CTL + ALT + DEL	Paperclip	Type Format [ENTER] at C prompt	Paperclip – when “Waiting...” appears press ESC + SPACE
FALCON 34X 48 Key	CTL + ALT + DEL	Paperclip	Type Format [ENTER] at C prompt	Paperclip – when “Waiting...” appears press ESC + SPACE
JET	FN1 + SCAN + PWR	F1 + F2 + SCAN + PWR	COLD BOOT, press ESC + 0	-
PT2000 4.73	-	-	Remove battery Press Alpha + Enter Insert battery	-
PT40 5.70	Reset barcode in the PRG manual	-	Remove battery Press CLR + ENT Insert battery	-

Thank you!

This presentation contains statements that are neither reported financial results nor other historical information. These statements are forward-looking statements. These forward-looking statements rely on a number of assumptions and are subject to a number of risks and uncertainties, many of which are outside the control of Datalogic S.p.A., that could cause actual results to differ materially from those expressed in or implied by such statements, such as future market conditions, currency fluctuations, the behavior of other market participants and the actions of governmental and state regulators.

© 2012 Datalogic ADC, Inc. • All rights reserved. Protected to the fullest extent under U.S. and international laws. Copying, or altering of this document is prohibited without express written consent from Datalogic ADC, Inc. • Product specifications are subject to change without notice. • Datalogic and the Datalogic logo are registered trademarks of Datalogic S.p.A. in many countries, including the U.S. and the E.U.. Datalogic ADC and the Datalogic Automatic Data Capture logo are trademarks of Datalogic S.p.A. • All other brand and product names are trademarks of their respective owners.

 **DATALOGIC**
AUTOMATIC DATA CAPTURE