

Wireless(BT) Pocket 2D Scanner

- MS926 -



User's Manual

Version 1.9

Change Log

Date	Change Description	Version
20161028	first published version	1.0
20170202	Update contents	1.1
2017426 / 2017523	Add BC logo and update NFC setting	1.2
2017626	Add frequency	1.3
20170823	Update 4.10 Lookup table function	1.4
20170927	Update Data Validation	1.5
2017116	Update BT pairing information	1.6
2019/1/8	Update SPEC	1.7
2019/2/19	Update Indicator defaults	1.8
2019/4/19	Add Data Terminator	1.9

Preface

About This Manual

Thank you for purchasing the unitech product.

This manual explains how to install, operate and maintain our product.

No part of this publication may be reproduced or used in any form, or by any electrical or mechanical means, such as photocopying, recording, or information storage and retrieval systems, without permission in writing from the manufacturer. The material in this manual is subject to change without notice. All product and company names are trademarks, service marks, or registered trademarks of their respective owners.

Regulatory Compliance Statements



FCC Warning Statement

This device has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference with radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference with radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.

- Increase the separation between the equipment and receiver.
 - Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
 - Consult the dealer or an experienced radio/TV technician for help.
1. This transmitter must not be co-located or operating in conjunction with any other antenna or transmitter.
 2. This device complies with FCC RF radiation exposure limits set forth for an uncontrolled environment. To maintain compliance with FCC RF exposure requirements, avoid direct contact to the transmitting antenna during transmitting.
 3. Any changes or modifications (including the antennas) made to this device that are not expressly approved by the manufacturer may void the user's authority to operate the equipment.

Operation on the 5.15 - 5.25GHz frequency band is restricted to indoor use only. The FCC requires indoor use for the 5.15-5.25GHz band to reduce the potential for harmful interference to co-channel Mobile Satellite Systems. Therefore, it will only transmit on the 5.25-5.35 GHz, 5.47-5.725 GHz and 5.725 - 5.850 GHz band when associated with an access point (AP).

FCC Label Statement

This device complies with part 15 of the FCC rules. Operation is subject to the following two conditions:

1. This device may not cause harmful interference.
2. This device must accept any interference received, including interference that may cause undesired operation.

RF Radiation Exposure Statement

For body contact during operation, this device has been tested and meets FCC RF exposure guidelines when used with an accessory that contains no metal and that positions the handset a minimum of 1.5 cm from the body. Use of other accessories may not ensure compliance with FCC RF exposure guidelines.

Canadian Compliance Statement

This Class B Digital apparatus meets all requirements of the Canadian Interference-Causing Equipment Regulations.

Cet appareil numérique de la classe B respecte les exigences du Règlement sur le matériel brouilleur du Canada.

European Conformity Statement

unitech Electronics co., Ltd herewith declares that the unitech product is in compliance with the essential requirements and all other provisions of the RED 2014/53/EU directive, the EMC 2014/30/EU directive and the Low Voltage 2014/35/EU directive.

The declaration of conformity is available for download at :

<https://portal.unitech.eu/public/Safetyregulatorystatement>

CE RF Exposure Compliance

This device meets EU requirements (2014/53/EU) on the limitation of exposure of the general public to electromagnetic fields by way of health protection.

For body-worn operation, this device has been tested and meets the ICNIRP guidelines and the European Standard EN 62209-2, for use with dedicated accessories, SAR is measured with this device at a separation of 0.5 cm to the body, while transmitting at the highest certified output power level in all frequency bands of this device. Use of other accessories which contain metals may not ensure compliance with ICNIRP exposure guidelines.

CE Mark Warning



This equipment complies with the requirements of Directive 2014/53/EU of the European Parliament and Commission from 24 May, 2014 governing Radio and Telecommunications Equipment and mutual recognition of conformity.

RoHS Statement



This device conforms to RoHS (Restriction of Hazardous Substances) European Union regulations that set maximum concentration limits on hazardous materials used in electrical and electronic equipment.

Waste electrical and electronic equipment (WEEE)



unitech has set up a policy and process to meet the EU directive 2002/96/EC and update 2003/108/EC concerning electronic waste disposal.

For more detailed information of the electronic waste disposal of the products you have purchased from unitech directly or via unitech's resellers, you shall either contact your local supplier or visit us at :

<https://portal.unitech.eu/public/WEEE>

Taiwan NCC Warning Statement

低功率電波輻射性電機管理辦法

第十二條：經型式認證合格之低功率射頻電機，非經許可，公司、商號或使用者均不得擅自變更頻率、加大功率或變更原設計之特性及功能。

第十四條：低功率射頻電機之使用不得影響飛航安全及干擾合法通信；經發現有干擾現象時，應立即停用，並改善至無干擾時方得繼續使用。

低功率射頻電機需忍受合法通信或工業、科學及醫療用電波輻射性電機設備之干擾。

注意事項：

1. 使用過度恐傷害視力。
2. 使用30分鐘請休息10分鐘；2歲以下幼兒不看螢幕，2歲以上每天看螢幕不要超過1小時。
3. 減少電磁波影響，請妥適使用。

Laser Information

The unitech product is certified in the U.S. to conform to the requirements of DHHS/CDRH 21CFR Subchapter J and to the requirements of IEC 825-1. Class II and Class 2 products are not considered to be hazardous. The unitech product contains internally a Visible Laser Diode (VLD) whose emissions do not exceed the maximum limits as set forth in the above regulations. The scanner is designed so that there is no human access to harmful laser light during normal operation, user maintenance or prescribed service operations.

The laser safety warning label required by the DHHS/IEC for the unitech product's optional laser scanner module is located on the memory compartment cover, on the back of the unit.

* Laser information only applies to the products with laser components.

CAUTION! Use of controls or adjustments or performance of procedures other than those specified herein may result in hazardous laser light. Use of optical instruments with the scanner, including binoculars, microscopes, and magnifying glasses, with will increase eye damage. This does not include eyeglasses worn by the user.

LED Information

The unitech product contains LED indicator(s) or LED ring whose luminance is not harmful to human eyes during normal operation, user maintenance or prescribed service operations.

*LED information only applies to the products with LED components.

Battery Notice

1. To guarantee optimal performance, it is recommended that rechargeable batteries be replaced every year, or after 500 charging cycles are completed. It is normal for the battery to balloon or expand after one year or 500 cycles. Although it does not cause damage, it cannot be used again and must be disposed of according to the location's safe battery disposal procedures.
2. If a battery performance decreases more than 20%, the battery is at the end of its life cycle. Stop use and ensure the battery is disposed of properly.
3. The length of time that a battery lasts depends on the battery type and how the device is used. Conserve the battery life by doing the following:
 - Avoid fully uncharging the battery because this places additional strain on it. Several partial uncharges with frequent charges are better than a fully uncharged battery. Charging a partially charged battery does not cause harm to the unit.
 - Keep the battery cool. Avoid hot vehicles. For prolonged storage, keep the battery at a 40% charge level.
 - Do not leave the battery uncharged and unused for an extended period of time, the battery will wear out and the longevity of the battery will be at least half of one with frequent charges.
4. Protect battery life by not over or under charging the battery.
5. Please do not leave battery unused for long time without charging it. Despite unitech's safety precautions, the battery pack may begin to change shape. If so, stop using it immediately. Please check to see if you are using a proper power adapter to charge the battery or contact your service provider for service.
6. If you cannot charge the battery after it has been idle for an extended period of time and it begins to heat up, please do not try to charge it. It may not be functional anymore.
7. Please only use the original battery from unitech. Using a third party battery can damage our products. Please note that when such damage occurs, it is not covered by your warranty.

CAUTION!

- RISK OF EXPLOSION IF BATTERY IS REPLACED INCORRECTLY.
DISPOSE OF USED BATTERIES ACCORDING TO THE INSTRUCTIONS.
- 如果更換不正確之電池行事會有爆炸的風險
請依製造商說明書處理用過之電池
- 如果更換不正確之電池行事會有爆炸的風險
請依製造商說明書處理用過之電池

Battery charge notice

It is important to consider temperature when the battery pack is charging. Charging is most efficient at normal room temperature or in a slightly cooler environment. It is essential that batteries are charged within the stated range of 0°C to 40°C. Charging batteries outside of the specified range could damage the batteries and shorten their life cycle.

CAUTION! Do not charge batteries at a temperature lower than 0°C. This will and make the batteries unstable and dangerous. Please use a battery temperature detecting device for a charger to ensure a safe charging temperature range.

CAUTION! To ensure the unit working properly, please keep all connectors away from the contaminants staying inside of them such as dust, grease, mud, and water. The negligence may cause the unit with no communication, short circuited, overheated and so on.

CAUTION! If the connector is damaged, please ensure the connector is being fully repaired before use the unit to avoid causing short circuited.

Storage and safety notice

Although charged batteries may be left unused for several months, their capacity may be depleted due to build up of internal resistance. If this happens, they will require recharging prior to use. Batteries may be stored at temperatures between -20°C to 60°C, however they may deplete more rapidly at higher temperatures. It is recommended to store batteries at room temperature.

** The message above only applies to the usage of the removable batteries.
For the products with non-removable batteries / without batteries, please refer to the specification of each product.*

Product Operation and Storage Notice

The unitech product has applicable operation and storage temperature conditions. Please follow the limitation of suggested temperature conditions to avoid failure, damage or malfunction.

** For applicable temperature conditions, please refer to the specification of each product.*

Adapter Notice

1. Please do not leave the power adapter in the socket when it is not connected to your unitech product for charging.
2. Please remove the power adapter when the battery is fully recharged.
3. The bundled power adapter that comes with your unitech product is not meant to be used outdoors. An adapter exposed to water or rain, or a very humid environment can cause damage to both the adapter and the product.
4. Please only use the bundled power adapter or same specification of adapter to charge your unitech product. Using the wrong power adapter can damage your unitech product.

** The message above only applies to the product connected to the adapter.
For the products without using the adapters, please refer to the specification of each product.*

Hearing Damage Warning

Zx.3 Warning

The warning shall be placed on the equipment, or on the packaging, or in the instruction manual and shall consist of the following:

- the symbol of Figure 1 with a minimum height of 5 mm; and
- the following wording, or similar :

To prevent possible hearing damage, do not listen at high volume levels for long periods.



Figure 1 – Warning label (IEC 60417-6044)

Alternatively, the entire warning may be given through the equipment display during use, when the user is asked to acknowledge activation of the higher level.

Worldwide Support

unitech's professional support team is available to quickly answer questions or assist with technical-related issues. Should an equipment problem occur, please contact the nearest unitech regional service representative.

For complete contact information please visit the Web sites listed below:

Taipei, Taiwan – Headquarters Tel: +886-2-89121122 E-mail: info@hq.ute.com Address: 5F, No. 136, Lane 235, Baoqiao Road, Xindian District, New Taipei City 231, Taiwan (R.O.C.) Website: http://www.ute.com	Europe Tel: +31-13-4609292 E-mail: info@eu.ute.com Address: Kapitein Hatterasstraat 19, 5015 BB, Tilburg, the Netherlands Website: http://eu.ute.com
China Tel: +86-59-2310-9966 E-mail: info@cn.ute.com Address: Room401C, 4F, RIHUA International Mansion, Xinfeng 3rd Road, Huoju Hi-tech District, Xiamen, Fujan , China Website: http://cn.ute.com	Japan Tel: +81-3-35232766 E-mail: info@jp.ute.com Address: Kayabacho Nagaoka Building 8F.,1-5-19 Shinkawa, Chuo-Ku, Tokyo, 104-0033, Japan Website: http://jp.ute.com
Asia & Pacific / Middle East Tel: +886-2-27911556 E-mail: info@apac.ute.com info@india.ute.com info@mideast.ute.com Address: 4F., No. 236, ShinHu 2nd Rd., NeiHu Chiu, 114, Taipei,Taiwan Website: http://apac.ute.com / http://mideast.ute.com	Latin America Tel: +52-55-5171-0528 E-mail: info@latin.ute.com Address: 17171 Park Row, Suite 210 Houston, TX 77084USA (Rep.) Website: http://latin.ute.com
North America Tel: +1-714-8926400 E-mail: info@us.ute.com / info@can.ute.com Address: 6182 Katella Ave, Cypress, CA 90630, USA Website: http://us.ute.com	Please scan QR Code to visit us : 

Warranty Policy

The items covered under the unitech Limited Warranty are free from defects during normal use.

The warranty period is varied from each country. Please consult with your supplier or unitech local office for actual length of warranty period to your purchased product.

Warranty becomes void if equipment is modified, improperly installed or used, damaged by accident or neglect, or if any parts are improperly installed or replaced by the user.

Table of Contents

Preface.....	i
About This Manual	i
Regulatory Compliance Statements	i
Laser Information	vi
LED Information	vi
Battery Notice.....	vii
Adapter Notice.....	x
Hearing Damage Warning	x
Worldwide Support	xi
Warranty Policy	xii
Chapter 1 - Overview.....	1
1.1 Package	1
1.2 Scanner Detail	2
1.3 Specifications	3
1.4 Getting Started	6
1.5 Battery Charging	7
1.6 LED Indicator / Beeper Sequence	8
1.7 Display Menu Tree	9
Chapter 2 - Installation.....	19
2.1 Mobile Devices pairing with / without NFC	19
2.2 BT HID.....	21
2.3 BT SPP.....	22
2.4 BT SPP (Slave)	23
2.5 USB SPP	24
Chapter 3 – Symbology	25
3.1 All symbologies.....	25
3.2 Message Length Description	25
3.3 1D.....	26
3.4 2D.....	62
Chapter 4 – Command Settings.....	67





4.1 System setting	67
4.2 BT pairing	69
4.3 Output data transmit	70
4.4 BT Config	73
4.5 Beep & Vibration & Indicators	76
4.6 Scan mode / Parameter Selection	79
4.7 Prefix/Suffix selections	91
4.8 Data formatting	96
4.9 Data Validation	117
4.11 Manually set up	119
Appendix A – Symbology Charts	122
Appendix B – Programming Charts	127

Chapter 1 - Overview




1.1 Package

Please make sure the following contents are in the MS926 gift box.
If something is missing or damaged, please contact your unitech representative.

The standard package contents




			
MS926 Scanner	Quick Reference Guide	Micro USB to USB Cable	Hand Strap

Optional accessories

		
1-Slot Charging cradle	5-Slot Charging cradle	USB Adapter

NOTE: 1. The scanner's default power off time is 5 minutes.
2. Please charge scanner for at least 2 hours prior to initial use.
3. The barcode with an asterisk (*) which appears in the following chapters indicates that it is the default option for the corresponding setting.

1.2 Scanner Detail



1.3 Specifications

System																								
Display	1" OLED, 128 x 64																							
OS	Proprietary, Connect to host with Windows, Android and iOS																							
Memory	64 Kbytes SRAM / 2 MB Flash ROM																							
Key	3 Keys: Page Up, Page Down, Scan with power on/off feature																							
Optical & Performance																								
Receiving Device	CMOS sensor with 640 x 480 pixel resolution																							
Illumination & Aiming	White LED illumination; Red LED dot aimer																							
Motion Tolerance	Up to 100 cm/s (4 in/s) for13 mil UPC at optimal focus																							
Typical frame rate	30 frames per second																							
Skew Angle	±45																							
Pitch Angle	±45																							
Printing Contrast Scale	35% minimum print contrast ratio																							
Depth of Field (DOF PCS=80%)	<table><tr><td>SR</td><td>near</td><td>far</td></tr><tr><td>100% U.P.C.</td><td>55mm</td><td>280mm</td></tr><tr><td>Code 39, 5 mil</td><td>61mm</td><td>130mm</td></tr><tr><td>Code 39, 20 mil</td><td>60mm</td><td>380mm</td></tr><tr><td>PDF417, 6.7 mil</td><td>60mm</td><td>125mm</td></tr><tr><td>Data Matrix, 10 mil</td><td>60mm</td><td>130mm</td></tr><tr><td>QR, 20 mil</td><td>50mm</td><td>230mm</td></tr></table>			SR	near	far	100% U.P.C.	55mm	280mm	Code 39, 5 mil	61mm	130mm	Code 39, 20 mil	60mm	380mm	PDF417, 6.7 mil	60mm	125mm	Data Matrix, 10 mil	60mm	130mm	QR, 20 mil	50mm	230mm
SR	near	far																						
100% U.P.C.	55mm	280mm																						
Code 39, 5 mil	61mm	130mm																						
Code 39, 20 mil	60mm	380mm																						
PDF417, 6.7 mil	60mm	125mm																						
Data Matrix, 10 mil	60mm	130mm																						
QR, 20 mil	50mm	230mm																						

Functionality	
Symbologies	
1D Code	UPC-A, UPC-E, EAN-8, EAN-13, CODE 39, CODE 128, GS1 128 , I 2 of 5, NEC 2 of 5, CODE 93, Codabar, GS1DataBar Omn, GS1DataBar Ltd, GS1DataBar Exp, CODE 11, MSI, UPC-E1, S 2 of 5 Indus, S 2 of 5 IATA, Matrix 2 of 5
1D Postal Code	China Post, Korea Post
2D Code	QR Code, Data Matrix, Aztec Code, PDF417, Macro PDF417, Micro PDF417, MaxiCode, Codablock A, Codablock F, GS1 Composite, Han Xin Code
2D Postal Code	Australian Post, British Post, Canadian Pos, InfoMail, Intelligent Mail Bar Code, Japanese Post, KIX (Netherlands) Post, GS1 Composite, Korea Post, Planet Code, Postal, Postnet
Scan Mode	Trigger mode, Pulse mode, Flash mode, Continuous Mode, Buffer mode
Environmental	
ESD Protection	Functional after 8K Contact and 12K Air
Mechanical Shock	1.5m onto concrete (scanner only)
IP Rate	IP42
Operating Temperature	0°C to 50°C
Storage Temperature	-30°C to 70°C
Relative Humidity	95% non-condensing
Electrical	
Operation Voltage	DC 3V to 5V
Current Consumption	Operation mode: 400mAh, Standby mode: 160mAh
Battery Type	Rechargeable Li-ion battery
Battery Capacity	680 mAh
Battery Charging time	Fully charged in about 4 hours
Operating Time	5 hours at condition of 1 scan/5 sec


Communication			
Radio Frequency		Bluetooth® V2.1+EDR.	
Protocol		Wireless SPP & HID profiles	
Range		Up to 30 Feet (Open space)	
Interface supported		Micro USB	
Mechanical			
Scanner Dimension		H21.1*W36.9*L95.9mm	
Scanner Weight		63g	
Switch life		10 million times	
Regulation Approvals			
CE, FCC, BSMI, VCCI			
Radio type / Description		Transmitter Frequency	Maximum Output Power
Bluetooth®	Bluetooth®	2400-2483.5MHz	3dBm

1.4 Getting Started


To turn on the scanner, press and hold the **Scan & Power Button** for about 2 seconds. To turn off the scanner, press and hold the **Scan & Power Button** for about 5 seconds.

After powering on, you will see the following screen on the scanner display. The scanner is now under standby mode. Now you can scan the desired barcode or start the BT pairing mode.


The standby display will show the current **Battery Status**, **Scanner Type**, **Operation Mode**, and **Time**.



The aiming beam can be **centered** over the bar code with any direction and have the proper alignment for a good read. (see example below)



1.5 Battery Charging



Insert the Micro USB connector into the port on the scanner and the standard USB connector of the USB cable into a USB port on the host PC.

1.6 LED Indicator / Beeper Sequence

Division	Action/Status	LED for Barcode reading & Communication	LED for Battery status	Beeper / Sound
Power On		Green & Red Lights blink once		One High Beep
Auto Power Off	Long press trigger key for 5 seconds			Three short beeps at 15 seconds before power off
USB connection				Low- Medium –High Beeps
USB disconnection				High- Medium –Low Beeps
Barcode reading	Wedge & Auto (When BT Connect)	Green Light blinks once		One Beep
	Batch	Green Light blinks once		One short Beep
	Wedge & Auto (When BT Disconnect)	Green Light blinks once		One short Beep
Data sent to PC	Data sent to PC successfully (Batch)	Green Light blinks once		Dee-Du sound
	Fail sent data to PC (Batch)	Red Light blinks once		Dee-Dee-Dee sound
Data delete		Green Light blinks once		
All Data delete		Deleting- Green light always on		
BT connection				Low- Medium –High Beeps
BT disconnection				High- Medium –Low Beeps
Low Battery Alarm (<10%)	(USB charging cable disconnected)		Blinking Red Light	
Battery charging	(USB charging cable connected)		Red light always on	
Battery Fully charged	(USB charging cable connected)		Green light always on	

1.7 Display Menu Tree

To enter main menu of MS926, press and hold Page Down key and then press Page Up key. (During one handed operation, you can press the area in between Page Down key and Page Up key to enter the main menu.)

You will see the following screen on the MS926 display. Now you can use **Page Up/Down button** to scroll through the menu and use **Scan button** to make your selection.



The **Display Menu Tree** below is based on Auto Mode.

Top Menu	Sub Menu Level 1	Sub Menu Level 2/Options/Result	Options/Result	Default Setting
General Setting	1. Scanner Type	1.1 BT HID	n/a	BT HID
		1.2 USB SPP		
		1.3 BT SPP		
		1.4 BT SPP (Slave)		
	2. Operation Mode	2.1 Wedge Mode	n/a	Auto Mode
		2.2 Batch Mode		
		2.3 Auto Mode		
	3. Date/Time	3.1 View Date/Time	Show Date/Time	2014-01-01
		3.2 Set Date/Time	Set Date/Time	08:00:00
		3.3 Time Display	3.3.1 Auto	Auto
			3.3.2 Always	
		3.4 Exit	n/a	
	4. Power Manager	4.1 Power Saving	Disable/30/20/15 /10/5 Sec.	15 Sec.
		4.2 Auto Power Off	Disable/30/20/15 /10/5/3/1 Min.	15 Min.

Top Menu	Sub Menu Level 1	Sub Menu Level 2/Options/Result	Options/Result	Default Setting
		4.3 Exit	n/a	
	5. Setup By Label	5.1 Enable	n/a	Enable
		5.2 Disable		
	6. FAC Default	6.1 Restore to FAC Default? Yes/No	Save to Selected Customer Setting	n/a
	7. FW Version	7.1 Show Firmware Version V0.x	n/a	
	8. Serial Number	8.1 Show SERIAL NUMBER XXXXXXXXXX	n/a	n/a
	9. Exit	n/a	n/a	n/a

Top Menu	Sub Menu Level 1	Sub Menu Level 2/Options/Result	Options/Result	Default Setting
Data & Memory	1. View / Edit Buff.	1.1. Show Buffer Data	1.1.1 Exit / Erase/ View	<p>■ If choose Exit, back to DATA/ MEMORY Page</p> <p>■ If choose Erase, delete data</p> <p>■ If choose View, continue to view the buffer data</p> <p>■ For Auto/Batch mode, pressing [ENTER]+[Down] / [ENTER]+[UP] keys to view data longer than 3 lines</p>

Top Menu	Sub Menu Level 1	Sub Menu Level 2/Options/Result	Options/Result	Default Setting
	2. Erase Buffer	2.1. Erase Buffer Yes/ No	Erase entry if Yes selected	
	3. Free MEM Space	3.1 Show FREE BUFFER MEM	n/a	
	4. Data Separator	4.1 CR		CR
		4.2 None		
		4.3 TAB		
		4.4 CRLF		
		4.5 LF		
	5. Sending BlkDly	5.1 Sending BlkDelay 10ms/3 Sec./1 Sec./500 ms./100 ms./50 ms.		10ms
	6. Date/Time Stamp	6.1 DATE STAMP Disable/DDMMYYYY/ DD.MM.YYYY/ DD/MM/YYYY/ DD--MM--YYYY/ MMDDYYYY/ MM.DD.YYYY/ MM/DD/YYYY/ MM-DD-YYYY/ YYYYMMDD/ YYYY.MM.DD/ YYYY/MM/DD/ YYYY-MM-DD		Disable

Top Menu	Sub Menu Level 1	Sub Menu Level 2/Options/Result	Options/Result	Default Setting
		6.2 TIME STAMP Disable/HHMMAM/ HHMM/ HH:MM AM/ HH:MM/HHMMSSAM/ HHMMSS/ HH:MM:SS AM/ HH:MM:SS		Disable
	7. Data Validation	7.1 Disable	Disable /Enable	Disable
		7.2 1:N Checking	CHECKING START POSITION	CHECKING LENGTH
		7.2 1:1 Checking	CHECKING START POSITION	CHECKING LENGTH
		7.3 Lookup Table	Download Lookup	
	8. Exit	n/a	n/a	n/a

Top Menu	Menu	Result	Default Setting
Bluetooth® CONFIG	1. BT Pairing	1.1 Pairing	
	2. MAC Address	2.1 12 Characters Bluetooth® MAC Address	
	3. Paired Device	3.1 Show PAIRED DEV NAME Show PAIRED DEV ADDR	
	4. Remove Pair	4.1 Remove pair	
	5. Signal Strength	5.1 Signal Strength Detection Enable / Disable	Enable
	6. BT FW Version	6.1 Show BT FW VERSION	
	7. Exit		

Top Menu	Menu	Result	Result	Default Setting
Beep & Vibrate	1. Beeper Volume	1.1 Medium/ Low/ Mute/ High		Medium
	2. Vibrator	2.1 Disable/ Enable		Disable
	3. Indicators	3.1 Good Read	3.1.1 Beeper & Vibrator Vibrator / Beeper None	Beeper
		3.2 Connection	3.2.1 Beeper & Vibrator Vibrator / Beeper None	Beeper
		3.3 Button	3.3.1 Beeper & Vibrator Vibrator / Beeper None	Beeper
		3.4 System Setting	3.4.1 Beeper & Vibrator Vibrator / Beeper None	Beeper
		3.5 System Warn/ Err	3.5.1 Beeper & Vibrator Vibrator / Beeper None	Beeper
		3.6 PwrOn	3.6.1 Beeper & Vibrator Vibrator / Beeper None	Beeper
		3.7 PwrOff Alarm	3.7.1 Beeper & Vibrator Vibrator / Beeper None	Beeper
		3.8 Checking Pass	3.8.1 1:1 / 1:N Checking Pass Indicator	Beeper & Vibrator
		3.9 Checking Fail	3.9.1 1:1 / 1:N Checking Fail Indicator	Beeper & Vibrator
		3.10 Exit	n/a	n/a
	4. Exit	n/a	n/a	n/a

Top Menu	Menu	Options	Options	Default Setting
Barcode Setting	1. Disable All 1D	OFF/ON		OFF
	2. 1D CODE SETTING	2.1 UPC-A	Enabled/Disabled	Enabled
		2.2 UPC-E	Enabled/Disabled	Enabled
		2.3 EAN-8	Enabled/Disabled	Enabled
		2.4 EAN-13	Enabled/Disabled	Enabled
		2.5 CODE 39	Enabled/Disabled	Enabled
		2.6 CODE 128	Enabled/Disabled	Enabled
		2.7 GS1 128	Enabled/Disabled	Enabled
		2.8 I 2 of 5	Enabled/Disabled	Enabled
		2.9 NEC 2 of 5	Enabled/Disabled	Enabled
		2.10 CODE 93	Enabled/Disabled	Enabled
		2.11 Codabar	Enabled/Disabled	Enabled
		2.12 GS1DataBar Omn	Enabled/Disabled	Enabled
		2.13 GS1DataBar Ltd	Enabled/Disabled	Enabled
		2.14 GS1DataBar Exp	Enabled/Disabled	Enabled
		2.15 CODE 11	Enabled/Disabled	Disabled
		2.16 MSI	Enabled/Disabled	Disabled
		2.17 UPC-E1	Enabled/Disabled	Disabled
		2.18 S 2 of 5 Indus	Enabled/Disabled	Disabled
		2.19 S 2 of 5 IATA	Enabled/Disabled	Disabled
		2.20 Matrix 2 of 5	Enabled/Disabled	Disabled
		2.21 Exit	Enabled/Disabled	
	3. 1D POSTAL CODE SETTING	3.1 China Post	Enabled/Disabled	Disabled
		3.2 Korea Post	Enabled/Disabled	Disabled
		3.3 Exit	Enabled/Disabled	
	4. Disable All 2D	OFF/ON		OFF
	5. 2D CODE SETTING	5.1 QR Code	Enabled/Disabled	Enabled
		5.2 Data Matrix	Enabled/Disabled	Enabled

Top Menu	Menu	Options	Options	Default Setting
		5.3 Aztec Code	Enabled/Disabled	Enabled
		5.4 PDF417	Enabled/Disabled	Enabled
		5.5 Macro PDF417	Enabled/Disabled	Enabled
		5.6 Micro PDF417	Enabled/Disabled	Disabled
		5.7 MaxiCode	Enabled/Disabled	Disabled
		5.8 Codablock A	Enabled/Disabled	Disabled
		5.9 Codablock F	Enabled/Disabled	Disabled
		5.10 GS1 Composite	Enabled/Disabled	Disabled
		5.11 Han Xin Code	Enabled/Disabled	Disabled
		5.12 Exit	Enabled/Disabled	
	6. 2D POSTAL CODE SETTING	6.1 OFF		OFF
		6.2 Australian	Enabled/Disabled	Disabled
		6.3 British	Enabled/Disabled	Disabled
		6.4 Canadian	Enabled/Disabled	Disabled
		6.5 China Post	Enabled/Disabled	Disabled
		6.6 InfoMail	Enabled/Disabled	Disabled
		6.7 Intelligent Mail	Enabled/Disabled	Disabled
		6.8 Japanese	Enabled/Disabled	Disabled
		6.9 KIX	Enabled/Disabled	Disabled
		6.10 Planet	Enabled/Disabled	Disabled
		6.11 Postal-4i	Enabled/Disabled	Disabled
		6.12 Postnet	Enabled/Disabled	Disabled
		6.13 Postnet w/B&B'	Enabled/Disabled	Disabled

Top Menu	Menu	Options	Options	Default Setting
		6.14 InfoMail British	Enabled/Disabled	Disabled
		6.15 Intelligent Mail Postnet w/B&B'	Enabled/Disabled	Disabled
		6.16 Postnet Postal-4i	Enabled/Disabled	Disabled
		6.17 Postnet Intelligent Mail	Enabled/Disabled	Disabled
		6.18 Postal-4i Intelligent Mail	Enabled/Disabled	Disabled
		6.19 Postal-4i Postnet w/B&B'	Enabled/Disabled	Disabled
		6.20 Planet Postnet	Enabled/Disabled	Disabled
		6.21 Planet Postnet w/B&B'	Enabled/Disabled	Disabled
		6.22 Planet Postal-4i	Enabled/Disabled	Disabled
		6.23 Planet Intelligent Mail	Enabled/Disabled	Disabled
		6.24 Planet Postnet Postal-4i	Enabled/Disabled	Disabled
		6.25 Planet Postnet Intelligent Mail	Enabled/Disabled	Disabled
		6.26 Planet Postal-4i Intelligent Mail	Enabled/Disabled	Disabled
		6.27 Postnet Postal-4i Intelligent Mail	Enabled/Disabled	Disabled
		6.28 Planet Postal-4i Postnet w/B&B'	Enabled/Disabled	Disabled
		6.29 Planet Intelligent Mail Postnet w/B&B'	Enabled/Disabled	Disabled
		6.30 Postal-4i Intelligent Mail Postnet w/B&B'	Enabled/Disabled	Disabled

Top Menu	Menu	Options	Options	Default Setting
		6.31 Planet Postal-4i Intelligent Mail Postnet	Enabled/Disabled	Disabled
		6.32 Planet Postal-4i Intelligent Mail Postnet w/B&B'	Enabled/Disabled	Disabled
	7. Exit	n/a	n/a	n/a

Top Menu	Sub Menu Level 1	Result	Default Setting
HID KEYBOARD SETTING	1. iOS Soft Keypad	1.1 iOS SOFT KEYPAD by DbIClick Disable / Enable	Disable
	2. KBD Language	2.1 US English / Japanese / Partial ALT Danish/ ALT Mode/ French / German Italian / Norwegian / Spanish / Swedish/ Swiss/ UK English	US English
	3. KBD Case	3.1 Auto Trace / Upper/ Lower	Auto Trace
	4. KBD ChrDelay	4.1 1ms/ 100ms/ 50ms/ 20ms/ 10ms/ 5ms	1ms
	5. Exit	n/a	n/a

Top Menu	Menu	Result	Default Setting
Remote SETTING	1. exit		

Chapter 2 - Installation

2.1 Mobile Devices pairing with / without NFC

2.1.1 Mobile Devices pairing with NFC

1. Ensure your mobile device supports NFC and that it is enabled.
2. It will automatically enter BT pairing mode.
(For firmware version older than 2.4, please hold Page Down key and Scan button simultaneously to enter BT pairing mode.)
3. Turn both NFC & Bluetooth® on your mobile device.
4. Touch the back of the MS926 scanner to your mobile phone, until the device prompts to accept pairing.
5. Press ok to respond your Bluetooth® pairing request.
6. MS926 is now connected to your mobile phone.

For NFC setting video, please check on our website :

http://tw.ute.com/products_info.php?pc1=3&pc2=296&rbu=0&pid=1807

2.1.2 Mobile Devices pairing without NFC

1. Go to your host device settings and turn the Bluetooth[®] function on.
2. MS926 will automatically enter BT pairing mode. (For firmware version older than 2.4, please hold Page Down key and Scan button simultaneously to enter BT pairing mode.)
3. The MS926 will appear on your device as "MS926-XXXXXX."
4. Select "MS926-XXXXXX."
5. If you have Bluetooth[®] 2.1 or higher, "MS926-XXXXXX" will now appear as paired.
6. If you are prompted to enter a pincode, please enter the number "2926" to finish pairing.

2.1.3 Pairing with PC / Notebook

1. Open "Devices and Printers" by clicking the Start button and then, on the Start menu, clicking Devices and Printers.
2. MS926 will automatically enter BT pairing mode. (For firmware version older than 2.4, please hold Page Down key and Scan button simultaneously to enter BT pairing mode.)
3. Click "Add a device," and then follow the instructions.
4. Click the Bluetooth[®] enabled device (MS926-[XXXXXX]) you want to add to your computer, and then click Next. If you don't see the device you want to add, make sure the device is turned on and discoverable. If you just turned on the device, it may take Windows several seconds to detect it.

2.2 BT HID

BT HID*



Establishing BT connection in BT HID mode.

1. Use MS926 to scan BT HID barcode.
2. It will automatically enter BT pairing mode.
(For firmware version older than 2.4, please hold Page Down key and Scan button simultaneously to enter BT pairing mode.)
3. Double-click **Bluetooth® Device** icon in the toolbar on your PC. Select **Add New Devices**. When you see a device list windows, choose MS926-XXXX and then press **Next**. PC now is establishing BT connection.
4. MS926 will beep when your PC successfully establish a BT connection with MS926.

2.3 BT SPP




Establishing BT connection in BT SPP mode.

1. To establish BT connection between MS926 and your PC in **BT SPP** mode, you must install unitech CDC driver on your PC in advance.
(For CDC driver, please check on the product section on unitech website : <http://www.ute.com>)
2. Use MS926 to scan **BT SPP** barcode.
3. It will automatically enter BT pairing mode.
(For firmware version older than 2.4, please hold Page Down key and Scan button simultaneously to enter BT pairing mode.)
4. Double-click **Bluetooth® Device** icon in the toolbar on your PC. Select **Add New Devices**. When you see a device list windows, choose MS926-XXXX and then press **Next**..
5. When PC is establishing a BT connection in **BT SPP** mode with MS926, windows system will automatically install the required drivers.
6. Back to your PC toolbar, right click on the **Bluetooth® Device** icon, choose **Open Settings**. Go to **COM Port** page and select in-coming COM port ;for example *COM 28*.
7. MS926 will beep when your PC successfully establish a BT connection with MS926.

2.4 BT SPP (Slave)

BT SPP (Slave)



Establishing BT connection in BT SPP (Slave) mode.

1. To establish a BT connection between MS926 and your PC in **BT SPP (Slave)** mode, you must install unitech CDC Driver on your PC in advance.
(For CDC driver, please check on the product section on unitech website : <http://www.ute.com>)
2. Use MS926 to scan **BT SPP (Slave)** barcode.
3. It will automatically enter BT pairing mode.
(For firmware version older than 2.4, please hold Page Down key and Scan button simultaneously to enter BT pairing mode.)
4. Double-click **Bluetooth® Device** icon in the toolbar on your PC. Select **Add New Devices**. When you see a device list windows, choose MS926-XXXX and then press **Next**.
5. When PC is establishing a BT connection in **BT SPP (Slave)** mode with MS926, windows system will automatically install the required drivers.
6. Back to your PC toolbar, right click on the **Bluetooth® Device** icon, choose **Open Settings**. Go to **COM Port** page and select out-going COM port; for example *COM 27*.
7. MS926 will beep when your PC successfully establish a BT connection with MS926.

2.5 USB SPP



Establishing connection in USB SPP mode.

1. To establish connection between MS926 and your PC in **USB SPP** mode, you must install unitech CDC Driver on your PC in advance.
(For CDC driver, please check on the product section on unitech website : <http://www.ute.com>)
2. Use MS926 to scan **USB SPP** barcode.
3. Connect MS926 to your PC with a Micro USB-USB cable.
4. Go to PC device manager to check the COM information, for example; *CDC USB Demonstration (COM40)*.
5. Back to the application, and select the corresponding COM port number.
MS926 will beep when your pc successfully establish the connection with MS926.

Chapter 3 – Symbology

3.1 All symbologies

If you want to decode all the symbologies allowable for your scanner, scan the **All Symbologies On** code. If on the other hand, you want to decode only a particular symbology, scan **All Symbologies Off** followed by the On symbol for that particular symbology.

Note: Scanner performance may reduce by scanning All Symbologies On.

Only scan All Symbologies On when needed.

Note : When All Symbologies On is scanned, 2D Postal Codes are not enabled. 2D Postal Codes must be enabled separately.

All Symbologies On



All Symbologies Off



3.2 Message Length Description

You are able to set the valid reading length of some of the bar code symbologies. You may wish to set the same value for minimum and maximum length to force the scanner to read fixed length bar code data.

This helps reduce the chances of a misread.

EXAMPLE: Decode only those bar codes with a count of 9-20 characters.

Min. length = 09 Max. length = 20

EXAMPLE: Decode only those bar codes with a count of 15 characters.

Min. length = 15 Max. length = 15

For a value other than the minimum and maximum message length defaults, scan the bar codes included in the explanation of the symbology, then scan the digit value of the message length and Save bar codes on the [Programming Chart](#). The minimum and maximum lengths and the defaults are included with the respective symbologies.

3.3 1D

3.3.1 Codabar

Codabar On*



Default All Codabar Settings



Codabar Off



3.3.1.1 Codabar Start / Stop Characters

Start/Stop characters identify the leading and trailing ends of the bar code. You may either transmit, or not transmit Start/Stop characters.

Default = Don't Transmit.

Transmit



Don't Transmit*



3.3.1.2 Codabar Check Characters

Codabar check characters are created using different “modulos.” You can program the scanner to read only Codabar bar codes with Modulo 16 check characters. Default = No Check Character.

No Check Character indicates that the scanner reads and transmits bar code data with or without a check character.

When Check Character is set to **Validate and Transmit**, the scanner will only read Codabar bar codes printed with a check character, and will transmit this character at the end of the scanned data.

When Check Character is set to **Validate, but Don't Transmit**, the unit will only read Codabar bar codes printed with a check character, but will not transmit the check character with the scanned data.

No Check Character*



Validate Modulo 16, but Don't Transmit



Validate Modulo 16 and Transmit



3.3.1.3 Codabar Concatenation

Codabar supports symbol concatenation. When you enable concatenation, the scanner looks for a Codabar symbol having a “D” start character, adjacent to a symbol having a “D” stop character. In this case the two messages are concatenated into one with the “D” characters omitted.



Select Require to prevent the scanner from decoding a single “D” Codabar symbol without its companion. This selection has no effect on Codabar symbols without Stop/Start D characters.

On



Off*



Require



3.3.1.4 Codabar Message Length

Scan the bar codes below to change the message length. Refer to [Message Length Description](#) for additional information.

Minimum and Maximum lengths = 2-60.

Minimum Default = 4, Maximum Default = 60.

Minimum Message Length



Maximum Message Length



3.3.2 Code 39

Code 39 On*



Default All Code 39 Settings

Code 39 Off



3.3.2.1 Code 39 Start / Stop Characters

Start/Stop characters identify the leading and trailing ends of the bar code. You may either transmit, or not transmit Start/ Stop characters.

Default = Don't Transmit.

Transmit



Don't Transmit*



3.3.2.2 Code 39 Check Characters

No Check Character indicates that the scanner reads and transmits bar code data with or without a check character.

When Check Character is set to **Validate, but Don't Transmit**, the unit only reads Code 39 bar codes printed with a check character, but will not transmit the check character with the scanned data.

When Check Character is set to **Validate and Transmit**, the scanner only reads Code 39 bar codes printed with a check character, and will transmit this character at the end of the scanned data. Default = No Check Character.

No Check Character*



Validate , but Don't Transmit



Validate and Transmit



3.3.2.3 Code 39 Message Length

Scan the bar codes below to change the message length. Refer to [Message Length Description](#) for additional information.

Minimum and Maximum lengths = 0-48.

Minimum Default = 0, Maximum Default = 48.

Minimum Message Length



Maximum Message Length



3.3.2.4 Code 39 Append

This function allows the scanner to append the data from several Code 39 bar codes together before transmitting them to the host computer. When the scanner encounters a Code 39 bar code with the append trigger character(s), it buffers Code 39 bar codes until it reads a Code 39 bar code that does not have the append trigger. The data is then transmitted in the order in which the bar codes were read (FIFO). Default = Off.

Off *



On



3.3.2.4 Code 32 Pharmaceutical (PARAF)

Code 32 Pharmaceutical is a form of the Code 39 symbology used by Italian pharmacies. This symbology is also known as PARAF.

Note: Trioptic Code must be turned off while scanning Code 32 Pharmaceutical codes.

Off *



On



3.3.2.5 Full ASCIIIf

Full ASCII Code 39 decoding is enabled, certain character pairs within the bar code symbol will be interpreted as a single character.

For example: \$V will be decoded as the ASCII character SYN, and /C will be decoded as the ASCII character #. Default = Off.

NUL %U	DLE \$P	SP SPACE	0 0	@ %V	P P	' %W	p +P
SOH \$A	DC1 \$Q	! /A	1 1	A A	Q Q	a +A	q +Q
STX \$B	DC2 \$R	" /B	2 2	B B	R R	b +B	r +R
ETX \$C	DC3 \$S	# /C	3 3	C C	S S	c +C	s +S
EOT \$D	DC4 \$T	\$ /D	4 4	D D	T T	d +D	t +T
ENQ \$E	NAK \$U	% /E	5 5	E E	U U	e +E	u +U
ACK \$F	SYN \$V	& /F	6 6	F F	V V	f +F	v +V
BEL \$G	ETB \$W	' /G	7 7	G G	W W	g +G	w +W
BS \$H	CAN \$X	(/H	8 8	H H	X X	h +H	x +X
HT \$I	EM \$Y) /I	9 9	I I	Y Y	i +I	y +Y
LF \$J	SUB \$Z	^ /J	:	/Z	J J	Z Z	j +J z +Z
VT \$K	ESC %A	+ /K	;	%F	K K	[%K	k +K { %P
FF \$L	FS %B	, /L	<	%G	L L	\ %L	l +L %Q
CR \$M	GS %C	-	=	%H	M M] %M	m +M } %R
SO \$N	RS %D	.	>	%I	N N	^ %N	n +N ~ %S
SI \$O	US %E	/	? %J	O O	_ %O	o +O	DEL %T

Character pairs /M and /N decode as a minus sign and period respectively.
Character pairs /P through /Y decode as 0 through 9.

Off *



On



3.3.2.6 Code 39 Code Page

Code pages define the mapping of character codes to characters. If the data received does not display with the proper characters, it may be because the bar code being scanned was created using a code page that is different from the one the host program is expecting. If this is the case, scan the bar code below, select the code page with which the bar codes were created ([see ISO 2022/ISO 646 Character Replacements](#)), and scan the value and the Save bar code from the [Programming Chart](#). The data characters should then appear properly.

Code 39 Code Page



3.3.3 Interleaved 2 of 5

Interleaved 2 of 5 On*



Default All Interleaved 2 of 5 Settings



Interleaved 2 of 5 Off



3.3.3.1 Check digit

No Check Digit indicates that the scanner reads and transmits bar code data with or without a check digit. When Check Digit is set to Validate, but Don't Transmit, the unit only reads Interleaved 2 of 5 bar codes printed with a check digit, but will not transmit the check digit with the scanned data. When Check Digit is set to Validate and Transmit, the scanner only reads Interleaved 2 of 5 bar codes printed with a check digit, and will transmit this digit at the end of the scanned data. Default = No Check Digit.

No Check Digit*



Validate , but Don't Transmit



Validate and Transmit



3.3.3.2 Interleaved 2 of 5 Message Length

Scan the bar codes below to change the message length. Refer to [Message Length Description](#) for additional information.

Minimum and Maximum lengths = 2-80.

Minimum Default = 4, Maximum Default = 80.

Minimum Message Length



Maximum Message Length



3.3.4 Code 93

Code 93 On*



Default All Code 93 Settings



Code 93 Off



3.3.4.1 Code 93 Message Length

Scan the bar codes below to change the message length. Refer to [Message Length Description](#) for additional information. Minimum and Maximum lengths = 0-80. Minimum Default = 0, Maximum Default = 80.

Minimum Message Length



Maximum Message Length



3.3.4.2 Code 93 Append

This function allows the scanner to append the data from several Code 93 bar codes together before transmitting them to the host computer. When this function is enabled, the scanner stores those Code 93 bar codes that start with a space (excluding the start and stop symbols), and does not immediately transmit the data. The scanner stores the data in the order in which the bar codes are read, deleting the first space from each. The scanner transmits the appended data when it reads a Code 93 bar code that starts with a character other than a space. Default = Off.

Off *



On



3.3.4.3 Code 93 Code Page

Code pages define the mapping of character codes to characters. If the data received does not display with the proper characters, it may be because the bar code being scanned was created using a code page that is different from the one the host program is expecting. If this is the case, scan the bar code below, select the code page with which the bar codes were created ([see ISO 2022/ISO 646 Character Replacements](#)), and scan the value and the Save bar code from the [Programming Chart](#). The data characters should then appear properly.

Code 93 Code Page



3.3.5 Standard 2 of 5 Industrial (three-bar start/stop)

Standard 2 of 5

Industrial On



Default All Standard 2 of 5
Industrial Settings



Standard 2 of 5

Industrial Off*



3.3.5.1 Standard 2 of 5 Industrial Message Length

Scan the bar codes below to change the message length. Refer to [Message Length Description](#) for additional information. Minimum and Maximum lengths = 1-48. Minimum Default = 4, Maximum Default = 48.

Minimum Message Length



Maximum Message Length



3.3.6 Standard 2 of 5 IATA (two-bar start/stop)

Standard 2 of 5 IATA

Industrial On



Default All Standard 2 of 5
IATA Industrial Settings



Standard 2 of 5 IATA

Industrial Off*



3.3.6.1 Standard 2 of 5 IATA Message Length

Scan the bar codes below to change the message length. Refer to [Message Length Description](#) for additional information. Minimum and Maximum lengths = 1-48. Minimum Default = 4, Maximum Default = 48.

Minimum Message Length



Maximum Message Length



3.3.7 Matrix 2 of 5

Matrix 2 of 5 On



Default All Matrix 2 of 5
Settings

Matrix 2 of 5 Off*



3.3.7.1 Matrix 2 of 5 Message Length

Scan the bar codes below to change the message length. Refer to [Message Length Description](#) for additional information. Minimum and Maximum lengths = 1-80. Minimum Default = 4, Maximum Default = 80.

Minimum Message Length



Maximum Message Length



3.3.8 Code 11

Code 11 On



Default All Code 11 Settings



Code 11 Off*



3.3.8.1 Check Digits Required

This option sets whether 1 or 2 check digits are required with Code 11 bar codes. Default = Two Check Digits.

One Check Digit



Two Check Digits*



3.3.8.2 Code 11 Message Length

Scan the bar codes below to change the message length. Refer to [Message Length Description](#) for additional information. Minimum and Maximum lengths = 1-80. Minimum Default = 4, Maximum Default = 80.

Minimum Message Length



Maximum Message Length



3.3.9 Code 128

Code 128 On*



Default All Code 128
Settings



Code 128 Off



3.3.9.1 ISBT 128 Concatenation

In 1994 the International Society of Blood Transfusion (ISBT) ratified a standard for communicating critical blood information in a uniform manner. The use of ISBT formats requires a paid license. The ISBT 128 Application Specification describes 1) the critical data elements for labeling blood products, 2) the current recommendation to use Code 128 due to its high degree of security and its space-efficient design, 3) a variation of Code 128 that supports concatenation of neighboring symbols, and 4) the standard layout for bar codes on a blood product label. Use the bar codes below to turn concatenation on or off. Default =Off.

On



Off*



3.3.9.2 Code 128 Message Length

Scan the bar codes below to change the message length. Refer to [Message Length Description](#) for additional information. Minimum and Maximum lengths = 0-80. Minimum Default = 0, Maximum Default = 80.

Minimum Message Length



Maximum Message Length



3.3.9.3 Code 128 Append

This function allows the scanner to append the data from several Code 128 bar codes together before transmitting them to the host computer. When the scanner encounters a Code 128 bar code with the append trigger character(s), it buffers Code 128 bar codes until it reads a Code 128 bar code that does not have the append trigger. The data is then transmitted in the order in which the bar codes were read (FIFO). Default = On.

On*



Off



3.3.9.4 Code 128 Code Page

Code pages define the mapping of character codes to characters. If the data received does not display with the proper characters, it may be because the bar code being scanned was created using a code page that is different from the one the host program is expecting. If this is the case, scan the bar code below, select the code page with which the bar codes were created ([see ISO 2022/ISO 646 Character Replacements](#)), and scan the value and the Save bar code from the [Programming Chart](#). The data characters should then appear properly.

Code 128 Code Page



3.3.10 UPC-A

Code UPC-A On*



Default All UPC-A Settings



Code UPC-A Off



Note: To convert UPC-A bar codes to EAN-13, see [Convert UPC-A to EAN-13](#).

3.3.10.1 UPC-A Check Digit

This selection allows you to specify whether the check digit should be transmitted at the end of the scanned data or not. Default = On.

On*



Off



3.3.10.2 UPC-A Number System

The numeric system digit of a U.P.C. symbol is normally transmitted at the beginning of the scanned data, but the unit can be programmed so it will not transmit it. Default = On.

On*



Off



3.3.10.3 UPC-A Addenda

This selection adds 2 or 5 digits to the end of all scanned UPC-A data. Default = Off for both 2 Digit and 5 Digit Addenda.

2 Digit Addenda Off*



2 Digit Addenda On



5 Digit Addenda Off*



5 Digit Addenda On



3.3.10.4 UPC-A Addenda Required

When Required is scanned, the scanner will only read UPC-A bar codes that have addenda. You must then turn on a 2 or 5 digit addenda. Default = Not Required.

Not Required*



Required



3.3.10.5 UPC-A Addenda Separator

When this feature is on, there is a space between the data from the bar code and the data from the addenda. When turned off, there is no space. Default = On.

On *



Off



3.3.10.6 UPC-A/EAN-13 with Extended Coupon Code

Use the following codes to enable or disable UPC-A and EAN-13 with Extended Coupon Code. When left on the default setting (Off), the scanner treats Coupon Codes and Extended Coupon Codes as single bar codes. If you scan the Allow Concatenation code, when the scanner sees the coupon code and the extended coupon code in a single scan, it transmits both as one symbology. Otherwise, it transmits the first coupon code it reads. If you scan the Require Concatenation code, the scanner must see and read the coupon code and extended coupon code in a single read to transmit the data. No data is output unless both codes are read. Default = Off.

Off*



Allow Concatenation



Require Concatenation



3.3.11 UPC-E0

Most U.P.C. bar codes lead with the 0 number system. To read these codes, use the UPC-E0 On selection. If you need to read codes that lead with the 1 number system, use [UPC-E1](#). Default = On.

Code UPC-A On*



Default All UPC-E Settings



Code UPC-A Off



3.3.11.1 UPC-E0 Expand

UPC-E Expand expands the UPC-E code to the 12 digit, UPC-A format. Default = Off.

Off *



On



3.3.11.2 UPC-E0 Addenda Required

When Required is scanned, the scanner will only read UPC-E bar codes that have addenda. Default = Not Required.

Not Required *



Required



3.3.11.3 UPC-E0 Addenda Separator

When this feature is On, there is a space between the data from the bar code and the data from the addenda. When turned Off, there is no space.

Default = On.

On*



Off



3.3.11.4 UPC-E0 Check Digit

Check Digit specifies whether the check digit should be transmitted at the end of the scanned data or not. Default = On.

On*



Off



3.3.11.5 UPC-E0 Leading Zero

This feature allows the transmission of a leading zero (0) at the beginning of scanned data. To prevent transmission, scan Off. Default = On.

On*



Off



3.3.11.6 UPC-E0 Addenda

This selection adds 2 or 5 digits to the end of all scanned UPC-E data.

Default = Off for both 2 Digit Addenda and 5 Digit Addenda.

2 Digit Addenda Off*



2 Digit Addenda On



5 Digit Addenda Off*



5 Digit Addenda On



3.3.12 UPC-E1

Most U.P.C. bar codes lead with the 0 number system. For these codes, use [UPC-E0](#). If you need to read codes that lead with the 1 number system, use the UPC-E1 On selection. Default = Off.

Off*



On



3.3.13 EAN/JAN-13

EAN/JAN-13 On*



Default All EAN/JAN
Settings



EAN/JAN-13 Off



3.3.13.1 Convert UPC-A to EAN-13

When UPC-A Converted to EAN-13 is selected, UPC-A bar codes are converted to 13 digit EAN-13 codes by adding a zero to the front. When Do not Convert UPC-A is selected, UPC-A codes are read as UPC-A.

Do not Convert UPC-A*



UPC-A Converted to EAN-13



3.3.13.2 EAN/JAN-13 Check Digit

This selection allows you to specify whether the check digit should be transmitted at the end of the scanned data or not. Default = On.

On*



Off



3.3.13.3 EAN/JAN-13 Addenda

This selection adds 2 or 5 digits to the end of all scanned EAN/JAN-13 data.
Default = Off for both 2 Digit and 5 Digit Addenda.

2 Digit Addenda Off*



2 Digit Addenda On



5 Digit Addenda Off*



5 Digit Addenda On



3.3.13.4 EAN/JAN-13 Addenda Required

When Required is scanned, the scanner will only read EAN/JAN-13 bar codes that have addenda. Default = Not Required.

Not Required*



Required



3.3.13.5 EAN/JAN-13 Addenda Separator

When this feature is **On**, there is a space between the data from the bar code and the data from the addenda. When turned **Off**, there is no space.

Default = On.

Note: If you want to enable or disable EAN13 with Extended Coupon Code, refer to

[UPC-A/EAN-13 with Extended Coupon Code.](#)

On*



Off



3.3.14 EAN/JAN-8

EAN/JAN-8 On*



Default All EAN/JAN-8
Settings

EAN/JAN-8 Off



3.3.14.1 EAN/JAN-8 Check Digit

This selection allows you to specify whether the check digit should be transmitted at the end of the scanned data or not. Default = On.

On*



Off



3.3.14.2 EAN/JAN-8 Addenda

This selection adds 2 or 5 digits to the end of all scanned EAN/JAN-8 data.
Default = Off for both 2 Digit and 5 Digit Addenda.

2 Digit Addenda Off*



2 Digit Addenda On



5 Digit Addenda Off*



5 Digit Addenda On



3.3.14.3 EAN/JAN-8 Addenda Required

When Required is scanned, the scanner will only read EAN/JAN-8 bar codes that have addenda. Default = Not Required.

Not Required*



Required



3.3.14.4 EAN/JAN-8 Addenda Separator

When this feature is On, there is a space between the data from the bar code and the data from the addenda. When turned Off, there is no space.

Default = On.

On*



Off



3.3.15 MSI

MSI On



Default All MSI Settings



MSI Off *



3.3.15.1 MSI Check Character

Different types of check characters are used with MSI bar codes. You can program the scanner to read MSI bar codes with Type 10 check characters. Default = Validate Type 10, but Don't Transmit. When Check Character is set to Validate Type 10/11 and Transmit, the scanner will only read MSI bar codes printed with the specified type check character(s), and will transmit the character(s) at the end of the scanned data. When Check Character is set to Validate Type 10/11, but Don't Transmit, the unit will only read MSI bar codes printed with the specified type check character(s), but will not transmit the check character(s) with the scanned data.

Validate Type 10, but Don't Transmit*



Validate Type 10 and Transmit



Validate 2 Type 10 Characters, but Don't Transmit



Validate 2 Type 10 Characters and Transmit



Validate Type 11 then Type 10 Character, but Don't Transmit



Validate Type 11 then Type 10 Character and Transmit



Disable MSI Check Characters



3.3.15.2 MSI Message Length

Scan the bar codes below to change the message length. Refer to [Message Length Description](#) for additional information. Minimum and Maximum lengths = 4-48. Minimum Default = 4, Maximum Default = 48.

Minimum Message Length



Maximum Message Length



3.3.16 GS1 DataBar Omnidirectional

GS1 DataBar
Omnidirectional On*



Default All GS1 DataBar
Omnidirectional Settings



GS1 DataBar
Omnidirectional Off



3.3.17 GS1 DataBar Limited

GS1 DataBar Limited On*



Default All GS1 DataBar
Limited Settings



GS1 DataBar Limited Off



3.3.18 GS1 DataBar Expanded

GS1 DataBar Expanded On*



Default All GS1 DataBar
Expanded Settings



GS1 DataBar Expanded Off



3.3.18.1 GS1 DataBar Expanded Message Length

Scan the bar codes below to change the message length. Refer to [Message Length Description](#) for additional information. Minimum and Maximum lengths = 4-74. Minimum Default = 4, Maximum Default = 74.

Minimum Message Length



Maximum Message Length



3.3.19 PDF 417

PDF 417 On*



Default All PDF 417 Settings



PDF 417 Off



3.3.19.1 PDF417 Message Length

Scan the bar codes below to change the message length. Refer to [Message Length Description](#) for additional information. Minimum and Maximum lengths = 1-2750. Minimum Default = 1, Maximum Default = 2750.

Minimum Message Length



Maximum Message Length



3.3.20 QR Code

QR Code On*



Default All QR Code Settings



QR Code Off



3.3.20.1 QR Code Message Length

Scan the bar codes below to change the message length. Refer to [Message Length Description](#) for additional information. Minimum and Maximum lengths = 1-7089. Minimum Default = 1, Maximum Default = 7089.

Minimum Message Length



Maximum Message Length



3.3.20.2 QR Code Append

This function allows the scanner to append the data from several QR Code bar codes together before transmitting them to the host computer. When the scanner encounters an QR Code bar code with the append trigger character(s), it buffers the number of QR Code bar codes determined by information encoded in those bar codes. Once the proper number of codes is reached, the data is output in the order specified in the bar codes. Default = On.

On*



Off



3.3.20.3 QR Code Page

QR Code pages define the mapping of character codes to characters. If the data received does not display with the proper characters, it may be because the bar code being scanned was created using a code page that is different from the one the host program is expecting. If this is the case, scan the bar code below, select the code page with which the bar codes were created ([see ISO 2022/ISO 646 Character Replacements](#)), and scan the value and the Save bar code from the [Programming Chart](#). The data characters should then appear properly.

QR Code Page



3.3.21 Data Matrix

Data Matrix On*



Default All Data Matrix
Settings



Data Matrix Off



3.3.21.1 Data Matrix Message Length

Scan the bar codes below to change the message length. Refer to [Message Length Description](#) for additional information. Minimum and Maximum lengths = 1-3116. Minimum Default = 1, Maximum Default = 3116.

Minimum Message Length



Maximum Message Length



3.3.21.2 Data Matrix Code Page

Data Matrix Code pages define the mapping of character codes to characters. If the data received does not display with the proper characters, it may be because the bar code being scanned was created using a code page that is different from the one the host program is expecting. If this is the case, scan the bar code below, select the code page with which the bar codes were created ([see ISO 2022/ISO 646 Character Replacements](#)), and scan the value and the Save bar code from the [Programming Chart](#). The data characters should then appear properly.

Data Matrix Code Page



3.3.22 MaxiCode

MaxiCode On



Default All MaxiCode Settings



MaxiCode Off*



3.3.22.1 MaxiCode Message Length

Scan the bar codes below to change the message length. Refer to [Message Length Description](#) for additional information. Minimum and Maximum lengths = 1-150. Minimum Default = 1, Maximum Default = 150..

Minimum Message Length



Maximum Message Length



3.3.23 Chinese Sensible (Han Xin) Code

Han Xin On



Default All Han Xin Settings

Han Xin Off*



3.3.23.1 Han Xin Code Message Length

Scan the bar codes below to change the message length. Refer to [Message Length Description](#) for additional information. Minimum and Maximum lengths = 1-7833. Minimum Default = 1, Maximum Default = 7833.

Minimum Message Length



Maximum Message Length



3.4 2D

3.4.1 Postal Codes - 2D

The following lists the possible 2D postal codes, and 2D postal code combinations that are allowed. Only one 2D postal code selection can be active at a time. If you scan a second 2D postal code selection, the first selection is overwritten. Default = 2D Postal Codes Off.

2D Postal Codes Off



3.4.1.1 Single 2D Postal Codes

Australian Post On



British Post On



Canadian Post On



Intelligent Mail Bar Code On



Japanese Post On



KIX Post On



Planet Code On



Postal-4i On



Postnet On



Postnet with B and B' Fields On



InfoMail On



3.4.1.2 Combination 2D Postal Codes

InfoMail and British Post On



**Postal-4i and Postnet with B
and B' Fields On**



Postnet and Postal-4i On



Planet Code and Postal-4i On



**Postal-4i and Intelligent Mail Bar
Code On**



**Planet Code, Postnet, and
Postal-4i On**



Planet Code and Postnet On



**Planet Code, Postal-4i, and
Intelligent Mail Bar Code On**



**Intelligent Mail Bar Code and
Postnet with B and B' Fields On**



**Planet Code, Postal-4i, and
Postnet with B and B' Fields On**



**Postnet and Intelligent Mail Bar
Code On**



**Postal-4i, Intelligent Mail Bar
Code, and Postnet with B and
B' Fields On**



**Planet Code and Postnet with B
and B' Fields On**



**Planet Code, Postal-4i,
Intelligent Mail Bar Code, and
Postnet with B and B' Fields On**



**Planet Code and Intelligent Mail
Bar Code On**



**Planet Code, Postal-4i,
Intelligent Mail Bar Code, and
Postnet On**



**Planet Code, Postnet, and
Intelligent Mail Bar Code On**



**Postnet, Postal-4i, and
Intelligent Mail Bar Code On**



**Planet Code, Intelligent Mail Bar
Code, and Postnet with B and B'
Fields On**



3.4.1.3 China Post (Hong Kong 2 of 5)

China Post (Hong Kong 2 of 5) On



Default All China Post (Hong Kong 2 of 5) Settings

China Post (Hong Kong 2 of 5) Off*



3.4.1.4 China Post (Hong Kong 2 of 5) Message Length

Scan the bar codes below to change the message length. Refer to [Message Length Description](#) for additional information. Minimum and Maximum lengths = 2-80. Minimum Default = 4, Maximum Default = 80.

Minimum Message Length



Maximum Message Length



Chapter 4 – Command Settings

4.1 System setting

4.1.1 Default

Scan below bar code to restore the factory setting

Factory Default



4.1.2 Display FW version / Data Format

Scan below bar code to show the current F/W & BT version

FW version



Scan the bar code below to show current data format settings.

Data Format Settings




4.1.3 Auto Power Off

Scan below bar code to set the time frame for auto power off



4.1.4 Power Saving

Scan below bar code to set the time frame for power saving.



4.2 BT pairing

4.2.1 Enter Pairing mode

Scan below bar code to enter BT pairing mode



4.2.2 Paired device info.

Scan below bar code to show the current paired device information



4.2.3 Remove the pair

Scan below bar code to remove BT pair



4.3 Output data transmit

4.3.1 Auto mode

In this mode, when scanner is out off BT transmit range, the scanned data will be stored in the memory and transmit data automatically when back to in-range.

Auto mode*



4.3.1.1 Erase last memory entry

Scan below bar code to erase last scanned data in memory

Erased Last Memory Entry



4.3.1.2 Erase all data in buffer (Erase Memory)

Scan below bar code to erase all data in the memory

Erase Memory



4.3.1.3 Check buffer memory space

Scan below bar code to check buffer memory space

Free Memory Space



4.3.2 Wedge mode

In this mode, the data only transmit while the BT is connected

Wedge mode



4.3.3 Signal Strength Detection

The purpose of signal strength detection is to enhance the data transmission for a better stability. For example, if operating with the weak RF signal, strongly suggest to enable signal strength detection to avoid any data loss. Meanwhile, it will also slow down the transmission speed.

Disable Signal Strength Detection *



Enable Signal Strength Detection



4.3.4 Batch mode

In this mode, the scanned data will be stored in the memory all the time and transmit data only when BT is connected by scanned the “send batch” bar code



4.3.4.1 Send batch

Scan below bar code to send the stored data to host



4.3.4.2 Erase last memory entry

Scan below bar code to erase last scanned data in batch memory



4.3.4.3 Erase all data in batch (Erase memory)

Scan below bar code to erase all data in batch memory



4.3.4.4 Free batch memory space

Scan below bar code to check batch memory space



4.4 BT Config

4.4.1 HID keyboard block delay

In BT HID mode, scan below bar code to set the block delay time.
Default is 10ms.

10 ms *




50 ms



100 ms



500 ms



1 Sec.



3 Sec.



4.4.2 HID keyboard inter-character delay

In BT HID mode, scan below bar code to set inter-character delay time. Default is 1ms.

1 ms *



5 ms



10 ms



20 ms



50 ms



100 ms



4.4.3 HID keyboard Case

In BT HID mode, scan below bar code to change the alphabet case. Scan "to lower" barcode to output data in lower case; or scan "to upper" barcode to output data in upper case. Default setting: "auto trace" to have original scanned data transmitted.

Auto Trace *



To Lower




To Upper



4.4.4 HID keyboard language

In BT HID mode, scan below bar code to change keyboard language. Default is US English

US English *



UK English



Swiss



Swedish



Norwegian



Italian



German




French



Danish



Partial ALT



Japanese (OADG109)



Spanish



ALT Mode



4.5 Beep & Vibration & Indicators

4.5.1 Beep

Scan below bar code to adjust beep volume. Default: Medium volume

4.5.1.1 High volume



4.5.1.2 Medium volume *



4.5.1.3 Low volume



4.5.1.4 Mute



4.5.2 Vibration

The vibration is off in default. Scan below bar code to open vibration function



4.5.3 Beep & Vibration Setting manually


Please follow the steps to set up the Beep & Vibration.

- Main Menu → Beep & Vibrate → Indicators → Button

Beeper & Vibrator *
 → None
 Beeper
 Vibrator

4.5.4 Indicators

4.5.4.1 Good Read Indicator



4.5.4.2 Connection Indicator



4.5.4.3 Button Indicator



4.5.4.4 System Setting Indicator

Beeper *	Beeper & Vibrator	Vibrator	None

4.5.4.5 System Warning/Error Indicator

Beeper *	Beeper & Vibrator	Vibrator	None

4.5.4.6 Power On Indicator

Beeper *	Beeper & Vibrator	Vibrator	None

4.5.4.7 Power Off Alarm

Beeper *	Beeper & Vibrator	Vibrator	None

4.6 Scan mode / Parameter Selection

4.6.1 Manual Trigger Mode

When in manual trigger mode, the scanner scans until a bar code is read, or until the trigger is released.

Manual Trigger - Normal



4.6.1.1 LED Illumination - Manual Trigger

If you wish to set the illumination LED brightness, scan one of the bar codes below. This sets the LED illumination for the scan engine when the trigger is pressed. Default = High.

Note: The LEDs are like a flash on a camera. The lower the ambient light in the room, the brighter the LEDs need to be so the scan engine can “see” the bar codes.

High*



Medium



4.6.2 Serial Trigger Mode

You can activate the scan engine by pressing the trigger. When in serial mode, the scan engine scans until a bar code has been read or until the deactivate command is sent. The scan engine can also be set to turn itself off after a specified time has elapsed.

4.6.2.1 Read Time-Out

Use this selection to set a time-out (in milliseconds) of the scan engine's trigger when using serial commands to trigger the scan engine. Once the scan engine has timed out, you can activate the scan engine either by pressing the trigger or using a serial trigger command. After scanning the Read Time-Out bar code, set the time-out duration (from 0-300,000 milliseconds) by scanning digits on the [Programming Chart](#), then scanning Save. Default = 30,000 ms.

Read Time-Out



4.6.3 Presentation Mode

Presentation Mode uses ambient light to detect bar codes. The LED dims until a bar code is presented to the scanner, then the LED brightens to read the code. If the light level in the room is not high enough, Presentation Mode may not work properly. Scan the following bar code to program your scanner for Presentation Mode.

Presentation Mode



4.6.3.1 Idle Illumination - Presentation Mode

Scan one of the bar codes below to set the LED illumination for the scanner when it is in an idle state in Presentation Mode. Default = High.

Note: If you use one of the lower Idle Illumination settings, and there is not enough ambient light, the scanner may have difficulty detecting when a bar code is presented to it. If the scanner has difficulty "waking up" to read bar codes, you may need to set the Idle Illumination to a brighter setting.

Note: LED Illumination - Presentation Mode does not apply to Poor Quality PDF Codes or Mobile Phone Read Mode.

High*



4.6.3.2 Presentation Sensitivity

Presentation Sensitivity is a numeric range that increases or decreases the scan engine's reaction time to bar code presentation. To set the sensitivity, scan the Sensitivity bar code, then scan the degree of sensitivity (from 0-20) from the inside back cover, and Save. 0 is the most sensitive setting, and 20 is the least sensitive. Default = 1.

Sensitivity



4.6.3.3 Centering


Use Centering to narrow the scan engine's field of view to make sure that when the scanner is hand-held, it reads only those bar codes intended by the user. For instance, if multiple codes are placed closely together, centering will insure that only the desired codes are read. (Centering can be used in conjunction with Aimer Delay, for the most error-free operation in applications where multiple codes are spaced closely together. Using the Aimer Delay and Centering features, the scanner can emulate the operation of older systems, such as linear laser bar code scanners.) If a bar code is not touched by a predefined window, it will not be decoded or output by the scan engine. If centering is turned on by scanning Centering On, the scan engine only reads codes that pass through the centering window you specify using the Top of Centering Window and Bottom of Centering Window bar codes.

4.6.3.4 Presentation Centering

Use Presentation Centering to narrow the scanner's field of view when it is in the stand to make sure the scanner reads only those bar codes intended by the user. For instance, if multiple codes are placed closely together, Presentation Centering will insure that only the desired codes are read.

To adjust centering when the scanner is hand-held, [see Centering](#). If a bar code is not touched by a predefined window, it will not be decoded or output by the scanner. If Presentation Centering is turned on by scanning Presentation Centering On, the scanner only reads codes that pass through the centering window you specify using the Top of Presentation Centering Window, Bottom of Presentation Centering Window, Left, and Right of Presentation Centering Window bar codes. In the example below, the white box is the centering window. The centering window has been set to 20% left, 30% right, 8% top, and 25% bottom. Since Bar Code 1 passes through the centering window, it will be read. Bar Code 2 does not pass through the centering window, so it will not be read.

Note: A bar code needs only to be touched by the centering window in order to be read. It does not need to pass completely through the centering window.



Scan Presentation Centering On, then scan one of the following bar codes to change the top, bottom, left, or right of the centering window. Then scan the percent you want to shift the centering window using digits on the inside back cover of this manual. Scan Save. Default Presentation Centering = 40% for Top and Left, 60% for Bottom and Right.

Note: If you are taking images, you must set the In-Stand Sensor to Off. You may program a Streaming Presentation Mode (Normal, Enhanced, or Mobile Phone) you wish to use for in-stand scanning, and a Manual Trigger mode (Normal, Enhanced, or Mobile Phone) you wish to use for out-of-stand scanning. To do this, you must first scan the preferred Streaming Presentation mode (see below), then scan the [Manual Trigger mode](#) you want to use.

Presentation Centering On



Presentation Centering Off *



**Top of Presentation
Centering Window**



**Bottom of Presentation
Centering Window**



**Left of Presentation
Centering Window**



**Right of Presentation
Centering Window**



4.6.4 Poor Quality Codes

4.6.4.1 Poor Quality 1D Codes

This setting improves the scanner's ability to read damaged or badly printed linear bar codes. When Poor Quality 1D Reading On is scanned, poor quality linear bar code reading is improved, but the scanner's snappiness is decreased, making it less aggressive when reading good quality bar codes. This setting does not affect 2D bar code reading. Default = Poor Quality 1D Reading Off.

Poor Quality 1D Reading Off*



Poor Quality 1D Reading On



4.6.4.2 Poor Quality PDF Codes

This setting improves the scanner's ability to read damaged or badly printed PDF codes by combining information from multiple images. When Poor Quality PDF On is scanned, poor quality PDF code reading is improved, but the scanner's snappiness is decreased, making it less aggressive when reading good quality bar codes. This setting does not affect 1D bar code reading. Default = Poor Quality PDF Reading Off.

Poor Quality PDF Reading Off*



Poor Quality PDF Reading On



4.6.5 Mobile Phone Read Mode

When this mode is selected, your scanner is optimized to read bar codes from mobile phone or other LED displays. However, the speed of scanning printed bar codes may be slightly lower when this mode is enabled.

Note: To turn off Mobile Phone Read Mode, scan a Manual or [Serial Trigger Mode bar code](#).

Hand Held Scanning - Mobile Phone



Presentation Scanning - Mobile Phone



4.6.6 Hands Free Time-Out

The Scan Stand and Presentation Modes are referred to as “hands free” modes. If the scanner’s trigger is pulled when using a hands free mode, the scanner changes to manual trigger mode. You can set the time the scanner should remain in manual trigger mode by setting the Hands Free Time-Out. Once the time-out value is reached, (if there have been no further trigger pulls) the scanner reverts to the original hands free mode. Scan the **Hands Free Time-Out** bar code, then scan the time-out duration (from 0-300,000 milliseconds) from the inside back cover, and Save. Default = 5,000 ms.

Hands Free Time-Out



4.6.7 Reread Delay

This sets the time period before the scan engine can read the same bar code a second time. Setting a reread delay protects against accidental rereads of the same bar code. Longer delays are effective in minimizing accidental rereads. Use shorter delays in applications where repetitive bar code scanning is required. Reread Delay only works when in a [Presentation Mode](#).
Default = Medium.

Short (500 ms)



Medium (750 ms)*



Long (1000 ms)



Extra Long (2000 ms)



4.6.8 Aimer On/ Off

This feature allows you to turn the aimer on and off. When the Interlaced bar code is scanned, the aimer is interlaced with the illumination LEDs. Default = Interlaced.

Interlaced*



Off



4.6.9 No Read

With No Read turned On, the scan engine notifies you if a code cannot be read. If using an EZConfig-Scanning Tool Scan Data Window, an "NR" appears when a code cannot be read. If No Read is turned Off, the "NR" will not appear. Default = Off.

If you want a different notation than "NR," for example, "Error," or "Bad Code," you can edit the output message ([see Data Formatting](#)). The hex code for the No Read symbol is 9C.

Off*



On



4.6.10 Video Reverse

Video Reverse is used to allow the scan engine to read bar codes that are inverted. The **Video Reverse Off** bar code below is an example of this type of bar code. Scan **Video Reverse Only** to read only inverted bar codes. Scan **Video Reverse and Standard Bar Codes** to read both types of codes.

*Note: After scanning **Video Reverse Only**, menu bar codes cannot be read. You must scan **Video Reverse Off** or **Video Reverse and Standard Bar Codes** in order to read menu bar codes.*

Note: Images downloaded from the unit are not reversed. This is a setting for decoding only.

Video Reverse Off *



Video Reverse and Standard Bar Codes





Video Reverse Only



4.6.11 Working Orientation

Some bar codes are direction-sensitive. For example, KIX codes and OCR can misread when scanned sideways or upside down. Use the working orientation settings if your direction-sensitive codes will not usually be presented upright to the scanner. Default = Upright.



4.7 Prefix/Suffix selections

4.7.1 To Add a Prefix or Suffix

Step 1. Scan the Add Prefix or Add Suffix symbol.

Step 2. Determine the 2 digit Hex value from the [Symbology Chart \(included in the Symbology Charts\)](#) for the symbology to which you want to apply the prefix or suffix. For example, for Code 128, Code ID is “j” and Hex ID is “6A”.

Step 3. Scan the 2 hex digits from the Programming Chart or scan 9, 9 for all symbologies.

Step 4. Determine the hex value from the [ASCII Conversion Chart \(Code Page 1252\)](#), for the prefix or suffix you wish to enter.

Note: To add the Code I.D., scan 5, C, 8, 0.

To add AIM I.D., scan 5, C, 8, 1.

To add a backslash (\), scan 5, C, 5, C.

To add a backslash (\) as in Step 7, you must scan 5C twice – once to create the leading backslash and then to create the backslash itself.

Step 5. Scan the 2 digit hex value from the Programming Chart.

Step 6. Repeat Steps 4 and 5 for every prefix or suffix character.

Step 7. Scan Save to exit and save, or scan Discard to exit without saving.

Repeat Steps 1-6 to add a prefix or suffix for another symbology.

Example: Add a Tab Suffix to All Symbologies :

Step 1. Scan Add Suffix.

Step 2. Scan 9, 9 from [the Programming Chart](#) to apply this suffix to all symbologies.

Step 3. Scan 0, 9 from [the Programming Chart](#). This corresponds with the hex value for a horizontal tab, shown in the [ASCII Conversion Chart \(Code Page 1252\)](#).

Scan Save, or scan Discard to exit without saving.

4.7.2 To Clear One or All Prefixes or Suffixes

You can clear a single prefix or suffix, or clear all prefixes/suffixes for a symbology. If you have been entering prefixes and suffixes for single symbologies, you can use Clear One Prefix (Suffix) to delete a specific character from a symbology. When you Clear All Prefixes (Suffixes), all the prefixes or suffixes for a symbology are deleted.

Step 1. Scan the Clear One Prefix or Clear One Suffix symbol.

Step 2. Determine the 2 digit Hex value from the [Symbology Chart \(included in the Symbology Charts\)](#) for the symbology from which you want to clear the prefix or suffix.

Step 3. Scan the 2 digit hex value from the Programming Chart or scan 9, 9 for all symbologies.

Your change is automatically saved.

4.7.3 To Add a Carriage Return Suffix to All Symbolologies

Scan the following bar code if you wish to add a carriage return suffix to all symbolologies at once. This action first clears all current suffixes, then programs a carriage return suffix for all symbolologies.

Add CR SuffixAll Symbolologies



Prefix Selections

Add Prefix



Clear All Prefixes



Clear One Prefix



Suffix Selections

Add Suffix



Clear One Suffix



Clear All Suffixes



4.7.4 Data Terminator

Scan the following bar code to set up data terminator.

CR*



None



CRLF



LF



TAB



4.7.5 Utilities

To Add a Test Code I.D. Prefix to All Symbologies

This selection allows you to turn on transmission of a Code I.D. before the decoded symbology. ([See the Symbology Charts](#)) for the single character code that identifies each symbology. This action first clears all current prefixes, then programs a Code I.D. prefix for all symbologies. This is a temporary setting that will be removed when the unit is power cycled.

Add Code I.D. Prefix to All Symbologies (Temporary)



Show Data Format

Scan the bar code below to show current data format settings.

Data Format Settings



4.8 Data formatting

4.8.1 Data Format Editor Introduction

You may use the Data Format Editor to change the scan engine's output. For example, you can use the Data Format Editor to insert characters at certain points in bar code data as it is scanned. The selections in the following pages are used only if you wish to alter the output. Default Data Format setting = None. Normally, when you scan a bar code, it is output automatically.

However, when you create a format, you must use a "send" command ([see Send Commands](#)) within the format program to output data. Multiple formats may be programmed into the scan engine. They are stacked in the order in which they are entered. However, the following list presents the order in which formats are applied:

1. Specific Terminal ID, Actual Code ID, Actual Length
2. Specific Terminal ID, Actual Code ID, Universal Length
3. Specific Terminal ID, Universal Code ID, Actual Length
4. Specific Terminal ID, Universal Code ID, Universal Length
5. Universal Terminal ID, Actual Code ID, Actual Length
6. Universal Terminal ID, Actual Code ID, Universal Length
7. Universal Terminal ID, Universal Code ID, Actual Length
8. Universal Terminal ID, Universal Code ID, Universal Length

The maximum size of a data format configuration is 2000 bytes, which includes header information. If a bar code is read that fails the first data format, the next data format, if there is one, will be used on the bar code data. If there is no other data format, the raw data is output. If you have changed data format settings, and wish to clear all formats and return to the factory defaults, scan the **Default Data Format** code below.

Default Data Format *



4.8.2 Add a Data Format

Step 1. Scan the Enter Data Format symbol.

Step 2. Select Primary/Alternate Format Determine if this will be your primary data format, or one of 3 alternate formats. This allows you to save a total of 4 different data formats. To program your primary format, scan 0 using the [Programming Chart](#). If you are programming an alternate format, scan 1, 2, or 3, depending on which alternate format you are programming. (See "Primary/Alternate Data Formats")

Step 3. Terminal Type Refer to [Terminal ID Table](#) and locate the Terminal ID number for your PC. Scan three numeric bar codes on the inside back cover to program the scan engine for your terminal ID (you must enter 3 digits). For example, scan 0 0 3 for an AT wedge. Note: 099 indicates all terminal types.

Step 4. Code I.D. In the [Symbology Charts](#), find the symbology to which you want to apply the data format. Locate the Hex value for that symbology and scan the 2 digit hex value from the [Programming Chart](#). If you wish to create a data format for all symbologies, with the exception of some specific symbologies, refer to [B8](#). If you are creating a data format for Batch Mode Quantity, use 35 for the Code I.D.
Note: 99 indicates all symbologies.

Step 5. Length
Specify what length (up to 9999 characters) of data will be acceptable for this symbology. Scan the four digit data length from the [Programming Chart](#). For example, 50 characters is entered as 0050.
Note: 9999 indicates all lengths.

Step 6. Editor Commands
Refer to [Data Format Editor Commands](#). Scan the symbols that represent the command you want to enter.

Step 7. Scan Save to save your data format, or Discard to exit without saving your changes.

Enter Data Format



Discard



Save



4.8.3 Other Programming Selections

Clear One Data Format

This deletes one data format for one symbology. If you are clearing the primary format, scan 0 from the [Programming Chart](#). If you are clearing an alternate format, scan 1,2, or 3, depending on the format you are clearing. Scan the Terminal Type and Code I.D. ([see Symbology Charts](#)), and the bar code data length for the specific data format that you want to delete. All other formats remain unaffected.

Clear all Data Formats This clears all data formats.

Save to exit and save your data format changes.

Discard to exit without saving any data format changes.

Clear One Data Format



Clear All Data Formats



Save



Discard



Terminal ID Table

Terminal	Model(s)	Terminal ID
USB	PC keyboard (HID)	124
	Mac Keyboard	125
	PC Keyboard (Japanese)	134
	Serial (COM driver required)	130
	HID POS	131
	USB SurePOS Handheld	128
	USB SurePOS Tabletop	129
Serial	RS232 TTL	000
	RS232 True	000
	RS485 (IBM-HHBCR 1+2, 46xx)	051
Keyboard	PS2 compatibles	003
	AT compatibles	002

4.8.4 Data Format Editor Commands

When working with the Data Format Editor, a virtual cursor is moved along your input data string. The following commands are used to both move this cursor to different positions, and to select, replace, and insert data into the final output.

4.8.4.1 Send Commands

■ Send all characters

F1 Include in the output message all of the characters from the input message, starting from current cursor position, followed by an insert character. Syntax = F1xx where xx stands for the insert character's hex value for its ASCII code. Refer to the [ASCII Conversion Chart \(Code Page 1252\)](#), for decimal, hex and character codes.

■ Send a number of characters

F2 Include in the output message a number of characters followed by an insert character. Start from the current cursor position and continue for "nn" characters or through the last character in the input message, followed by character "xx." Syntax = F2nnxx where nn stands for the numeric value (00-99) for the number of characters, and xx stands for the insert character's hex value for its ASCII code. Refer to the [ASCII Conversion Chart \(Code Page 1252\)](#), for decimal, hex and character codes.

F2 Example: Send a number of characters



Send the first 10 characters from the bar code above, followed by a carriage return. Command string: **F2100D**

F2 is the "Send a number of characters" command

10 is the number of characters to send

0D is the hex value for a CR

The data is output as: **1234567890**

F2 and F1 Example: Split characters into 2 lines

Send the first 10 characters from the bar code above, followed by a carriage return, followed by the rest of the characters.

Command string: **F2100DF10D**

F2 is the "Send a number of characters" command

10 is the number of characters to send for the first line

0D is the hex value for a CR

F1 is the "Send all characters" command

0D is the hex value for a CR

The data is output as:

1234567890

ABCDEFGHIJ

<CR>

■ Send all characters up to a particular character

F3 Include in the output message all characters from the input message, starting with the character at the current cursor position and continuing to, but not including, the search character "ss," followed by an insert character. The cursor is moved forward to the "ss" character. Syntax = **F3ssxx** where ss stands for the search character's hex value for its ASCII code, and xx stands for the insert character's hex value for its ASCII code. Refer to the [ASCII Conversion Chart \(Code Page 1252\)](#), for decimal, hex and character codes.

F3 Example: Send all characters up to a particular character



Using the bar code above, send all characters up to but not including "D," followed by a carriage return.

Command string: **F3440D**

F3 is the "Send all characters up to a particular character" command

44 is the hex value for a 'D'

0D is the hex value for a CR

The data is output as: **1234567890ABC**

<CR>

■ **Send all characters up to a string**

B9 Include in the output message all characters from the input message, starting with the character at the current cursor position and continuing to, but not including, the search string "s...s." The cursor is moved forward to the beginning of the "s...s" string. Syntax = B9nnnns...s where nnnn stands for the length of the string, and s...s stands for the string to be matched. The string is made up of hex values for the characters in the string. Refer to the [ASCII Conversion Chart \(Code Page 1252\)](#), for decimal, hex and character codes.

B9 Example: Send all characters up to a defined string



Using the bar code above, send all characters up to but not including "AB."

Command string: **B900024142**

B9 is the "Send all characters up to a string" command

0002 is the length of the string (2 characters)

41 is the hex value for A

42 is the hex value for B

The data is output as: **1234567890**

■ **Send all characters up to a string**

E9 Include in the output message all but the last “nn” characters, starting from the current cursor position. The cursor is moved forward to one position past the last input message character included. Syntax = E9nn where nn stands for the numeric value (00-99) for the number of characters that will not be sent at the end of the message.

■ **Insert a character multiple times**

F4 Send “xx” character “nn” times in the output message, leaving the cursor in the current position. Syntax = F4xxnn where xx stands for the insert character’s hex value for its ASCII code, and nn is the numeric value (00-99) for the number of times it should be sent. Refer to the [ASCII Conversion Chart \(Code Page 1252\)](#), for decimal, hex and character codes.

E9 and F4 Example: Send all but the last characters, followed by 2 tabs



Send all characters except for the last 8 from the bar code above, followed by 2 tabs.

Command string: **E908F40902**

E9 is the “Send all but the last characters” command

08 is the number of characters at the end to ignore

F4 is the “Insert a character multiple times” command

09 is the hex value for a horizontal tab

02 is the number of times the tab character is sent

The data is output as: **1234567890AB <tab><tab>**

■ Insert a string

BA Send "ss" string of "nn" length in the output message, leaving the cursor in the current position. Syntax = BAnnnns...s where nnnn stands for the length of the string, and s...s stands for the string. The string is made up of hex values for the characters in the string. Refer to [the ASCII Conversion Chart \(Code Page 1252\)](#), for decimal, hex and character codes.

B9 and BA Example: Look for the string "AB" and insert 2 asterisks (**)



Using the bar code above, send all characters up to but not including "AB." Insert 2 asterisks at that point, and send the rest of the data with a carriage return after.

Command string: **B900024142BA00022A2AF10D**

B9 is the "Send all characters up to a string" command

0002 is the length of the string (2 characters)

41 is the hex value for A

42 is the hex value for B

BA is the "Insert a string" command

0002 is the length of the string to be added (2 characters)

2A is the hex value for an asterisk (*)

2A is the hex value for an asterisk (*)

F1 is the "Send all characters" command

0D is the hex value for a CR

The data is output as:

1234567890ABCDEFGHIJ**

<CR>

■ Insert symbology name

- B3** Insert the name of the bar code's symbology in the output message, without moving the cursor. Only symbologies with [Symbology Charts](#). Refer to the [ASCII Conversion Chart \(Code Page 1252\)](#), for decimal, hex and character codes.

■ Insert bar code length

- B4** Insert the bar code's length in the output message, without moving the cursor. The length is expressed as a numeric string and does not include leading zeroes.

B3 and B4 Example: Insert the symbology name and length



Send the symbology name and length before the bar code data from the bar code above. Break up these insertions with spaces. End with a carriage return.

Command string: **B3F42001B4F42001F10D**

B3 is the "Insert symbology name" command

F4 is the "Insert a character multiple times" command

20 is the hex value for a space

01 is the number of times the space character is sent

B4 is the "Insert bar code length" command

F4 is the "Insert a character multiple times" command

20 is the hex value for a space

01 is the number of times the space character is sent

F1 is the "Send all characters" command

0D is the hex value for a CR

The data is output as:

Code128 20 1234567890ABCDEFGHIJ

<CR>

■ **Insert key strokes**

B5 Insert a key stroke or combination of key strokes. Key strokes are dependent on your keyboard. Any key can be inserted, including arrows and functions. Syntax = B5xxssnn where xx is the number of keys pressed (without key modifiers), ss is the key modifier from the table below, and nn is the key number.

Key Modifiers	
No Key Modifier	00
Shift Left	01
Shift Right	02
Alt Left	04
Alt Right	08
Control Left	10
Control Right	20

For example, B501021F inserts an "A" on a 104 key, U.S. style keyboard. B5 = the command, 01 = number of keys pressed (without the key modifier), 02 is the key modifier for Shift Right, and 1F is the "a" key. If a lower case "a" were to be inserted, B501001F would be entered.

If there are three keystrokes, the syntax would change from B5xxssnn for one keystroke to B5xxssnnssnnssnn. An example that would insert "abc" is as follows: B503001F00320030F833.

Note: Key modifiers can be added together when needed.

Example: Control Left+Shift Left = 11.

4.8.4.2 Move Commands

■ Move the cursor forward a number of characters

F5 Move the cursor ahead “nn” characters from current cursor position.

Syntax = F5nn where nn is the numeric value (00-99) for the number of characters the cursor should be moved ahead.

F5 Example: Move the cursor forward and send the data



Move the cursor forward 3 characters, then send the rest of the bar code data from the bar code above. End with a carriage return.

Command string: **F503F10D**

F5 is the “Move the cursor forward a number of characters” command

03 is the number of characters to move the cursor

F1 is the “Send all characters” command

0D is the hex value for a CR

The data is output as:

4567890ABCDEFGHIJ

<CR>

■ Move the cursor backward a number of characters

F6 Move the cursor back “nn” characters from current cursor position. Syntax = F6nn where nn is the numeric value (00-99) for the number of characters the cursor should be moved back.

■ Move the cursor to the beginning

F7 Move the cursor to the first character in the input message. Syntax = F7.

FE and F7 Example: Manipulate bar codes that begin with a 1



Search for bar codes that begin with a 1. If a bar code matches, move the cursor back to the beginning of the data and send 6 characters followed by a carriage return. Using the bar code above:

Command string: **FE31F7F2060D**

FE is the "Compare characters" command

31 is the hex value for 1

F7 is the "Move the cursor to the beginning" command

F2 is the "Send a number of characters" command

06 is the number of characters to send

0D is the hex value for a CR

The data is output as:

123456

<CR>

■ Move the cursor to the end

EA Move the cursor to the last character in the input message. Syntax = EA.

4.8.4.3 Search Commands

■ Search forward for a character

F8 Search the input message forward for "xx" character from the current cursor position, leaving the cursor pointing to the "xx" character. Syntax = F8xx where xx stands for the search character's hex value for its ASCII code. Refer to [the ASCII Conversion Chart \(Code Page 1252\)](#), for decimal, hex and character codes.

F8 Example: Send bar code data that starts after a particular character



Search for the letter "D" in bar codes and send all the data that follows, including the "D." Using the bar code above:

Command string: **F844F10D**

F8 is the "Search forward for a character" command

44 is the hex value for "D"

F1 is the "Send all characters" command

0D is the hex value for a CR

The data is output as:

DEFGHIJ

<CR>

■ **Search backward for a character**

F9 Search the input message backward for “xx” character from the current cursor position, leaving the cursor pointing to the “xx” character. Syntax = F9xx where xx stands for the search character’s hex value for its ASCII code. Refer to [the ASCII Conversion Chart \(Code Page 1252\)](#), for decimal, hex and character codes.

■ **Search forward for a string**

B0 Search forward for “s” string from the current cursor position, leaving cursor pointing to “s” string. Syntax = B0nnnnS where nnnn is the string length (up to 9999), and S consists of the ASCII hex value of each character in the match string. For example, B0000454657374 will search forward for the first occurrence of the 4 character string “Test.” Refer to the [ASCII Conversion Chart \(Code Page 1252\)](#), for decimal, hex and character codes.

B0 Example: Send bar code data that starts after a string of characters



Search for the letters “FGH” in bar codes and send all the data that follows, including “FGH.” Using the bar code above:

Command string: **B00003464748F10D**

B0 is the “Search forward for a string” command

0003 is the string length (3 characters)

46 is the hex value for “F”

47 is the hex value for “G”

48 is the hex value for “H”

F1 is the “Send all characters” command

0D is the hex value for a CR

The data is output as:

FGHIJ

<CR>

■ Search backward for a string

B1 Search backward for "s" string from the current cursor position, leaving cursor pointing to "s" string. Syntax = B1nnnnS where nnnn is the string length (up to 9999), and S consists of the ASCII hex value of each character in the match string. For example, B1000454657374 will search backward for the first occurrence of the 4 character string "Test." Refer to the [ASCII Conversion Chart \(Code Page 1252\)](#), for decimal, hex and character codes.

■ Search forward for a non-matching character

E6 Search the input message forward for the first non-"xx" character from the current cursor position, leaving the cursor pointing to the non-"xx" character. Syntax = E6xx where xx stands for the search character's hex value for its ASCII code. Refer to the [ASCII Conversion Chart \(Code Page 1252\)](#), for decimal, hex and character codes.

E6 Example: Remove zeroes at the beginning of bar code data



This example shows a bar code that has been zero filled. You may want to ignore the zeroes and send all the data that follows. E6 searches forward for the first character that is not zero, then sends all the data after, followed by a carriage return. Using the bar code above:

Command string: **E630F10D**

E6 is the "Search forward for a non-matching character" command

30 is the hex value for 0

F1 is the "Send all characters" command

0D is the hex value for a CR

The data is output as:

37692

<CR>

■ Search backward for a non-matching character

E7 Search the input message backward for the first non-“xx” character from the current cursor position, leaving the cursor pointing to the non-“xx” character. Syntax = E7xx where xx stands for the search character's hex value for its ASCII code. Refer to the [ASCII Conversion Chart \(Code Page 1252\)](#), for decimal, hex and character codes.

4.8.4.4 Miscellaneous Commands

■ Suppress characters

FB Suppress all occurrences of up to 15 different characters, starting at the current cursor position, as the cursor is advanced by other commands. When the FC command is encountered, the suppress function is terminated. The cursor is not moved by the FB command. Syntax = FBnnxxyy . .zz where nn is a count of the number of suppressed characters in the list, and xxyy .. zz is the list of characters to be suppressed.

FB Example: Remove spaces in bar code data



This example shows a bar code that has spaces in the data. You may want to remove the spaces before sending the data. Using the bar code above:

Command string: **FB0120F10D**

FB is the “Suppress characters” command

01 is the number of character types to be suppressed

20 is the hex value for a space

F1 is the “Send all characters” command

0D is the hex value for a CR

The data is output as:

34567890

<CR>

■ Stop suppressing characters

FC Disables suppress filter and clear all suppressed characters. Syntax = FC.

■ Replace characters

E4 Replaces up to 15 characters in the output message, without moving the cursor. Replacement continues until the E5 command is encountered.

Syntax = E4nnxx1xx2yy1yy2...zz1zz2 where nn is the total count of the number of characters in the list (characters to be replaced plus replacement characters); xx1 defines characters to be replaced and xx2 defines replacement characters, continuing through zz1 and zz2.

E4 Example: Replace zeroes with CRs in bar code data



If the bar code has characters that the host application does not want included, you can use the E4 command to replace those characters with something else. In this example, you will replace the zeroes in the bar code above with carriage returns.

Command string: **E402300DF10D**

E4 is the "Replace characters" command

02 is the total count of characters to be replaced, plus the replacement characters (0 is replaced by CR, so total characters = 2)

30 is the hex value for 0

0D is the hex value for a CR (the character that will replace the 0)

F1 is the "Send all characters" command

0D is the hex value for a CR

The data is output as:

1234

5678

ABC

<CR>

■ Stop replacing characters

E5 Terminates character replacement. Syntax = E5.

■ Compare characters

FE Compare the character in the current cursor position to the character "xx."
If characters are equal, move the cursor forward one position. Syntax =
FExx where xx stands for the comparison character's hex value for its
ASCII code. Refer to [the ASCII Conversion Chart \(Code Page 1252\)](#), for
decimal, hex and character codes.

■ Compare string

B2 Compare the string in the input message to the string "s." If the strings are
equal, move the cursor forward past the end of the string. Syntax =
B2nnnnS where nnnn is the string length (up to 9999), and S consists of
the ASCII hex value of each character in the match string. For example,
B2000454657374 will compare the string at the current cursor position
with the 4 character string "Test." Refer to [the ASCII Conversion Chart
\(Code Page 1252\)](#), for decimal, hex and character codes.

■ Check for a number

EC Check to make sure there is an ASCII number at the current cursor
position. The format is aborted if the character is not numeric.

EC Example: Only output the data if the bar code begins with a number


If you want only data from bar codes that begin with a number, you can use EC
to check for the number.


Command string: **ECF10D**

EC is the "Check for a number" command

F1 is the "Send all characters" command

0D is the hex value for a CR

If this bar code is read,  AB1234 the next data format, if there is one,
will be used on the data. If there is no other format, the format fails and the

raw data is output as **AB1234**. If this bar code is read:  1234AB the data
is output as: **1234AB**

<CR>

■ Check for non-numeric character

ED Check to make sure there is a non-numeric ASCII character at the current cursor position. The format is aborted if the character is numeric.

ED Example: Only output the data if the bar code begins with a letter

If you want only data from bar codes that begin with a letter, you can use ED to check for the letter.

Command string: **EDF10D**

ED is the "Check for a non-numeric character" command

F1 is the "Send all characters" command

0D is the hex value for a CR



If this bar code is read: 1234AB the next data format, if there is one, will be used on this data. If there is no other format, the format fails and the raw



data is output as **1234AB**. If this bar code is read: AB1234 the data is output as: **AB1234 <CR>**

■ Insert a delay

EF Inserts a delay of up to 49,995 milliseconds (in multiples of 5), starting from the current cursor position. Syntax = EFnnnn where nnnn stands for the delay in 5ms increments, up to 9999. This command can only be used with keyboard emulation.a

■ Discard Data

B8 Discards types of data. For example, you may want to discard Code 128 bar codes that begin with the letter A. In step 4 , select 6A (for Code 128), and in step 5, select 9999 (for all lengths). Enter FE41B8 to compare and discard Code 128 bar codes that begin with the letter A. Syntax = B8.

Note: The B8 command must be entered after all other commands. The Data Format must be Required in order for the B8 command to work. If Data Format is On, but Not Required,, bar code data that meets the B8 format is scanned and output as usual. Because the data format needs to be On and Required for the B8 command, you must input data formats for all bar codes you wish to discard as well as all bar codes you wish to output. Other data format settings impact the B8 command. If Data Format Non-Match Error Tone is On , the scan engine emits an error tone. If

Data format Non-Match Error Tone is Off, the code is disabled for reading and no tone is sounded.

4.8.5 Data Formatter

When Data Formatter is turned Off, the bar code data is output to the host as read, including prefixes and suffixes.

Data Formatter Off



You may wish to require the data to conform to a data format you have created and saved. The following settings can be applied to your data format:

Data Formatter On, Not Required, Keep Prefix/Suffix

Scanned data is modified according to your data format, and prefixes and suffixes are transmitted.

Data Formatter On, Not Required, Drop Prefix/Suffix

Scanned data is modified according to your data format. If a data format is found for a particular symbol, those prefixes and suffixes are not transmitted. If a data format is not found for that symbol, the prefixes and suffixes are transmitted.

Data Format Required, Keep Prefix/Suffix

Scanned data is modified according to your data format, and prefixes and suffixes are transmitted. Any data that does not match your data format requirements generates an error tone and the data in that bar code is not transmitted. If you wish to process this type of bar code without generating an error tone, see [Primary/Alternate Data Formats](#).

Data Format Required, Drop Prefix/Suffix

Scanned data is modified according to your data format. If a data format is found for a particular symbol, those prefixes and suffixes are not transmitted. Any data that does not match your data format requirements generates an error tone. If you wish to process this type of bar code without generating an error tone, see [Primary/Alternate Data Formats](#).

Choose one of the following options.

Default = Data Formatter On, Not Required, Keep Prefix/Suffix.

Data Formatter On, Not Required, Keep Prefix/Suffix *



Data Format Required, Keep Prefix/Suffix



4.8.6 Primary/Alternate Data Formats

You can save up to four data formats, and switch between these formats. Your primary data format is saved under 0. Your other three formats are saved under 1, 2, and 3. To set your device to use one of these formats, scan one of the bar codes below.

Primary Data Format



Data Format 1



Data Format 2



Data Format 3



4.9 Data Validation

There are three items on data validation :

- 1:N Checking : Use data 1 to check with multiple data continuously.
- 1:1 Checking : Use data 1 to check with single data .
- Lookup table : This function is to prevent users from entering wrong data. By inputting particular barcode to restrict scan results, MS926 lookup table function will scan only allowed barcode that make the data more accurately.

4.9.1 1:1 / 1:N function

To define 1:1/1:N function, please enter,

- 1) Main Menu /Data & Memory/ Data Validation.
- 2) Select "**1:1 Checking**" or "**1:N Checking**"
- 3) Select **CHECKING START POSITION** for Data 1 and Data 2
 - Data1 is valid data,
Start Position: 1--255
 - Data 2 is data to be checked with Data1,
Start Position: Any, 1--255
- 4) Select **CHECKING LENGTH** (All Characters, 1--255)
"All Characters" means from Data 1 start position to its end.
- 5) Enable/ Disable **PAUSE SCAN WHEN CHECKING FAIL.**
Once enabled this function, press page down key to exit when the screen shows checking fail.
- 6) Enable/ Disable **CHECKING SCREEN INDICATOR**
users can choose whether to display "X" or "○" on the screen when checking the data.
- 7) To reset all the setting, please choose **disable**.

4.9.2 Lookup Table Function

Following are Lookup table function information:

- Format: ASCII text format
- Items are terminated by CR or CRLF
- Sorted in 'A' -- 'Z' order automatically
- File-size limits: less than 256K bytes

4.9.2.1 Enable / Disable

Please follow the steps to enable/ disable this function.

Main Menu → Data & Memory → Data Validation → Lookup Table
→ Set Lookup

4.9.2.2 Download Lookup

Please follow the steps to download New Lookup Table or Check Current Lookup Table Name /Size.

1. Main Menu → Data & Memory → Data Validation → Lookup Table
→ Download Lookup
2. Connect MS926 to your PC with a Micro USB cable.
3. Go to PC device manager to check the COM information, for example; *CDC USB Demonstration (COM40)*.
4. Open serial communication tool and select the corresponding COM port number, for example; *CDC USB Demonstration (COM40)*.
And then choose the form you would like to upload.

4.9.2.3 Utility for Sorting Data

To download lookup table sorting utility, please click the link below to go to MS926 **download section**. It will help users to organize data by sorting it with efficiency.

http://eu.ute.com/products_info.php?pc1=3&pc2=296&rbu=0&pid=1807

4.11 Manually set up

4.11.1 Date / Time Stamp Setting

Please follow the steps to set up the Date & Time stamp.

Main Menu → Data & Memory → Date / Time Stamp → (see the following chart for Date / Time stamp Display)

Date / Time stamp Display

Date Stamp Settings	Time Stamp Settings	D/T Stamp Order	Data Entry Order	Field Delimiter
<i>Disable *</i> YYYY-MM-DD YYYY/MM/DD YYYY.MM.DD YYYYMMDD MM-DD-YYYY MM/DD/YYYY MM.DD.YYYY MMDDYYYY DD-MM-YYYY DD/MM/YYYY DD.MM.YYYY DDMMYYYY	<i>Disable *</i> HH:MM:SS HH:MM:SS AM HHMMSS HHMMSSAM HH:MM HH:MM AM HHMM HHMMAM	<Data> <Time> * <Time> <Data>	<Data> <Stamp> * <Stamp> <Data>	None Comma * Space Semicolon TAB

4.11.2 Hotkeys

- Hold and press [UP] and then press [SCAN] keys together will enable :

<u>1. In Batch Mode</u>	<u>2. In Auto Mode</u>	<u>3. A shortcut key to exit to main menu.</u>
<ul style="list-style-type: none"> • View/Edit Batch • Send Batch • Erase Batch • Free MEM Space 	<ul style="list-style-type: none"> • View/Edit Buffer • Erase Buffer • Free MEM Space 	

- iOS Soft Keypad

Please follow the steps to set up iOS Soft Keypad.

Main Menu → HID KBD Setting → iOS Soft Keypad by DbIClick [SCAN]

key → Enable *
Disable

4.11.3 Data View/Erase Function

Please follow the steps to view / erase data in Batch mode / Auto mode.

<u>1. In Batch Mode</u>	<u>2. In Auto Mode</u>
Main Menu → Data & Memory → Batch Data → Press trigger key → Exit → Erase View	Main Menu → Data & Memory → Buffer Data → Press trigger key → Exit → Erase View

4.11.4 Block Delay to BT SPP and USB SPP

Please follow the steps to send block delay to BT SPP and USB SPP.

Main Menu → Data & Memory → Sending BlkDly

10 ms *
50 ms-
→ 100 ms
500 ms
1 second
3 seconds

4.11.5 BT Signal Strength Detection Setting

Please follow the steps to detect BT signal strength.

Main Menu → Bluetooth® CFG → Signal Strength Detection

→ Enable *
Disable

4.11.6 BT Pairing by Scanning Barcode Label

Please set up a label format (`//.A<BT Address>`) and generate a barcode corresponding to it, scan the barcode for BT pairing.

Example 1: `//.A50b7c3b01939`

Example 2: `//.A50:B7:C3:B0:19:39`

Appendix A – Symbology Charts

“m” represents the AIM modifier character. Refer to International Technical Specification, Symbology Identifiers, for AIM modifier character details.

Prefix/Suffix entries for specific symbologies override the universal (All Symbologies, 99) entry.

Refer to Data Editing and Data Formatting for information about using Code ID and AIM ID.

Linear Symbologies

Symbology	AIM		Honeywell	
	ID	Possible modifiers (m)	ID	Hex
All Symbologies				99
Codabar]Fm	0-1	a	61
Code 11]H3		h	68
Code 128]Cm	0, 1, 2, 4	j	6A
Code 32 Pharmaceutical (PARAF)]X0		<	3C
Code 39 (supports Full ASCII mode)]Am	0, 1, 3, 4, 5, 7	b	62
TCIF Linked Code 39 (TLC39)]L2		T	54
Code 93 and 93i]Gm	0-9, A-Z, a-m	i	69
EAN]Em	0, 1, 3, 4	d	64
EAN-13 (including Bookland EAN)]E0		d	64
EAN-13 with Add-On]E3		d	64
EAN-13 with Extended Coupon Code]E3		d	64
EAN-8]E4		D	44
EAN-8 with Add-On]E3		D	44
GS1				
GS1 DataBar]em	0	y	79
GS1 DataBar Limited]em		{	7B
GS1 DataBar Expanded]em		}	7D
GS1-128]C1		l	49
2 of 5				
China Post (Hong Kong 2 of 5)]X0		Q	51
Interleaved 2 of 5]lm	0, 1, 3	e	65
Matrix 2 of 5]X0		m	6D
NEC 2 of 5]X0		Y	59
Straight 2 of 5 IATA]Rm	0, 1, 3	f	66
Straight 2 of 5 Industrial]S0		f	66
MSI]Mm	0, 1	g	67
Telepen]Bm		t	74
UPC		0, 1, 2, 3, 8, 9, A, B, C		

Symbology	AIM		Honeywell	
	ID	Possible modifiers (m)	ID	Hex
UPC-A	JE0		c	63
UPC-A with Add-On	JE3		c	63
UPC-A with Extended Coupon Code	JE3		c	63
UPC-E	JE0		E	45
UPC-E with Add-On	JE3		E	45
UPC-E1	JX0		E	45

Add Honeywell Code ID				5C80
Add AIM Code ID				5C81
Add Backslash				5C5C
Batch mode quantity			5	35

2D Symbologies

Symbology	AIM		Honeywell	
	ID	Possible modifiers (m)	ID	Hex
All Symbologies				99
Aztec Code	jzm	0-9, A-C	z	7A
Chinese Sensible Code (Han Xin Code)	JX0		H	48
Codablock A	JO6	0, 1, 4, 5, 6	V	56
Codablock F	JOm	0, 1, 4, 5, 6	q	71
Code 49	JTm	0, 1, 2, 4	l	6C
Data Matrix	jdM	0-6	w	77
GS1	Jem	0-3	y	79
GS1 Composite	Jem	0-3	y	79
GS1 DataBar Omnidirectional	Jem		y	79
MaxiCode	JUm	0-3	x	78
PDF417	JLm	0-2	r	72
MicroPDF417	JLm	0-5	R	52
QR Code	JQm	0-6	s	73
Micro QR Code	JQm		s	73

Postal Symbologies

Symbology	AIM		Honeywell	
	ID	Possible modifiers (m)	ID	Hex
All Symbologies				99
Australian Post	JX0		A	41
British Post	JX0		B	42
Canadian Post	JX0		C	43
China Post	JX0		Q	51
InfoMail	JX0		,	2c
Intelligent Mail Bar Code	JX0		M	4D
Japanese Post	JX0		J	4A
KIX (Netherlands) Post	JX0		K	4B
Korea Post	JX0		?	3F
Planet Code	JX0		L	4C
Postal-4i	JX0		N	4E
Postnet	JX0		P	50

ASCII Conversion Chart (Code Page 1252)

In keyboard applications, ASCII Control Characters can be represented in 3 different ways, as shown below. The CTRL+X function is OS and application dependent. The following table lists some commonly used Microsoft functionality. This table applies to U.S. style keyboards. Certain characters may differ depending on your Country Code/PC regional settings.

Non-printable characters			Keyboard Control + ASCII (CTRL+X) Mode		
ASCII control			Windows Mode Control + X Mode On (KBDCAS2)		
DEC	HEX	Char	Control + X Mode Off (KBDCAS0)	CTRL + X	CTRL + X function
0	00	NUL	Reserved	CTRL+ @	
1	01	SOH	NP Enter	CTRL+ A	Select all
2	02	STX	Caps Lock	CTRL+ B	Bold
3	03	ETX	ALT Make	CTRL+ C	Copy
4	04	EOT	ALT Break	CTRL+ D	Bookmark
5	05	ENQ	CTRL Make	CTRL+ E	Center
6	06	ACK	CTRL Break	CTRL+ F	Find
7	07	BEL	Enter / Ret	CTRL+ G	
8	08	BS	(Apple Make)	CTRL+ H	History
9	09	HT	Tab	CTRL+ I	Italic
10	0A	LF	(Apple Break)	CTRL+ J	Justify
11	0B	VT	Tab	CTRL+ K	hyperlink
12	0C	FF	Delete	CTRL+ L	list, left align
13	0D	CR	Enter / Ret	CTRL+ M	
14	0E	SO	Insert	CTRL+ N	New
15	0F	SI	ESC	CTRL+ O	Open
16	10	DLE	F11	CTRL+ P	Print
17	11	DC1	Home	CTRL+ Q	Quit
18	12	DC2	PrtScn	CTRL+ R	
19	13	DC3	Backspace	CTRL+ S	Save
20	14	DC4	Back Tab	CTRL+ T	
21	15	NAK	F12	CTRL+ U	
22	16	SYN	F1	CTRL+ V	Paste
23	17	ETB	F2	CTRL+ W	
24	18	CAN	F3	CTRL+ X	
25	19	EM	F4	CTRL+ Y	
26	1A	SUB	F5	CTRL+ Z	
27	1B	ESC	F6	CTRL+ [
28	1C	FS	F7	CTRL+ \	
29	1D	GS	F8	CTRL+]	
30	1E	RS	F9	CTRL+ ^	
31	1F	US	F10	CTRL+ -	
127	7F	␣	NP Enter		

ISO 2022/ISO 646 Character Replacements

Code pages define the mapping of character codes to characters. If the data received does not display with the proper characters, it may be because the bar code being scanned was created using a code page that is different from the one the host pro-gram is expecting. If this is the case, select the code page with which the bar codes were created. The data characters should then appear properly.

Code Page Selection Method/Country	Standard	Keyboard Country	Honeywell Code Page Option
United States (standard ASCII)	ISO/IEC 646-IRV	n/a	1
Automatic National Character Replacement	ISO/IEC 2022	n/a	2 (default)
Binary Code page	n/a	n/a	3
<i>Default "Automatic National Character replacement" will select the below Honeywell Code Page options for Code128, Code 39 and Code 93.</i>			
United States	ISO/IEC 646-06	0	1
Canada	ISO /IEC 646-121	54	95
Canada	ISO /IEC 646-122	18	96
Japan	ISO/IEC 646-14	28	98
China	ISO/IEC 646-57	92	99
Great Britain (UK)	ISO /IEC 646-04	7	87
France	ISO /IEC 646-69	3	83
Germany	ISO/IEC646-21	4	84
Switzerland	ISO /IEC 646-CH	6	86
Sweden / Finland (extended Annex C)	ISO/IEC 646-11	2	82
Ireland	ISO /IEC 646-207	73	97
Denmark	ISO/IEC 646-08	8	88
Norway	ISO/IEC 646-60	9	94
Italy	ISO/IEC 646-15	5	85
Portugal	ISO/IEC 646-16	13	92
Spain	ISO/IEC 646-17	10	90
Spain	ISO/IEC 646-85	51	91

Dec			35	36	64	91	92	93	94	96	123	124	125	126
Hex			23	24	40	5B	5C	5D	5E	60	7B	7C	7D	7E
US	0	1	#	\$	@	[\]	^	`	{		}	~
CA	54	95	#	\$	à	ä	ç	é	î	ô	é	ù	è	û
CA	18	96	#	\$	à	ä	ç	é	Ê	ô	é	ù	è	û
JP	28	98	#	\$	@	[¥]	^	`	{		}	~
CN	92	99	#	¥	@	[\]	^	`	{		}	~
GB	7	87	£	\$	@	[\]	^	`	{		}	~
FR	3	83	£	\$	à	°	ç	§	^	µ	é	ù	è	~
DE	4	84	#	\$	§	Ä	Ö	Ü	^	`	ä	ö	ü	ß
CH	6	86	ù	\$	à	é	ç	è	î	ô	ä	ö	ü	û
SE/FI	2	82	#	¤	É	Ä	Ö	Å	Ü	é	ä	ö	å	ü
DK	8	88	#	\$	@	Æ	Ø	Å	^	`	æ	ø	å	~
NO	9	94	#	\$	@	Æ	Ø	Å	^	`	æ	ø	å	~
IE	73	97	£	\$	Ó	É	Í	Ú	Á	ó	é	í	ú	á
IT	5	85	£	\$	§	°	ç	é	^	ù	à	ó	è	ì
PT	13	92	#	\$	§	Ã	Ç	Õ	^	`	ã	ç	õ	~
ES	10	90	#	\$	§	í	ñ	¿	^	`	°	ñ	¿	~
ES	51	91	#	\$	·	í	ñ	Ç	¿	·	·	ñ	¿	~
COUNTRY	Country Keyboard	Honeywell CodePage	ISO / IEC 646 National Character Replacements											

Appendix B – Programming Charts

0



1



2



3



4



5



6



7



8



9



A



B



C



D



E



F



Save



Discard



Reset

